

GENERAL ELECTRICAL NOTES:

ADMINISTRATIVE:

- 1. THE FOLLOWING ABBREVIATIONS SHALL APPLY TO NOTES AND PLANS: EC - PLUMBING CONTRACTOR, EC - ELECTRICAL CONTRACTOR, MC - MECHANICAL CONTRACTOR, GC - GENERAL CONTRACTOR, FASC - FIRE ALARM SYSTEM CONTRACTOR, AU - AUTHORITY HAVING JURISDICTION. 2. "PROVIDE" MEANS TO FURNISH AND INSTALL... 3. EC SHALL PROVIDE LABOR, MATERIALS, EQUIPMENT, AND SERVICES... 4. WORKMANSHIP SHALL BE IN ACCORDANCE WITH NECA 1 "STANDARD PRACTICE FOR GOOD WORKMANSHIP IN ELECTRICAL CONTRACTING"... 5. ALL MATERIALS AND EQUIPMENT SHALL BE DELIVERED TO THE SITE... 6. THE ELECTRICAL CONTRACTOR SHALL OBTAIN AND PAY FOR ALL PERMITS... 7. DO NOT SCALE THESE DRAWINGS-REFER TO ARCHITECTURAL SHEETS FOR DIMENSIONS... 8. TRADE NAMES AND MANUFACTURERS ARE SPECIFIED TO ESTABLISH A QUALITY STANDARD... 9. THE ELECTRICAL CONTRACTOR SHALL VISIT THE SITE PRIOR TO BIDDING... 10. GROUNDING AND BONDING SHALL BE PER NEC ARTICLE 250... 11. THE ELECTRICAL CONTRACTOR SHALL ALSO COORDINATE WITH THE GENERAL CONTRACTOR REGARDING THE BONDING OF THE FOOTING REBAR... 12. ALL MATERIALS AND EQUIPMENT SHALL COMPLY WITH THE UNDERWRITERS' LABORATORIES, INC. STANDARDS... 13. CONDUCTORS, FUSES, CIRCUIT BREAKERS, AND DISCONNECT SWITCHES SHOWN ON THESE PLANS HAVE BEEN SIZED FOR THE SPECIFIED EQUIPMENT... 14. THE ELECTRICAL CONTRACTOR SHALL COORDINATE WITH THE GENERAL CONTRACTOR TO ENSURE THE FOLLOWING MATERIALS ARE RECYCLED... 15. ALL WORK SHALL CONFORM TO 2020 NATIONAL ELECTRIC CODE, 2018 STATE BUILDING CODE, AND ALL APPLICABLE LOCAL CODES.

MATERIALS:

- 1. THE ELECTRICAL CONTRACTOR SHALL PROVIDE ALL NECESSARY DISCONNECTS, SWITCHES, RECEPTACLES, TERMINALS, ETC. UNDER THE ELECTRICAL BO AND SHALL INCLUDE ALL NECESSARY CIRCUITS AND CONNECTIONS TO THE EQUIPMENT PROVIDED BY ALL SUPPLIERS... 2. ELECTRICAL CONTRACTOR SHALL PROVIDE ALL SERVICE ENTRANCE EQUIPMENT, SUB PANELS, AND OTHER ELECTRICAL DISTRIBUTION EQUIPMENT AS NECESSARY FOR A COMPLETE INSTALLATION... 3. ENCLOSED SAFETY SWITCHES SHALL BE HEAVY DUTY TYPE BY SQUARE D, EATON, OR GE... 4. OCCUPANCY SENSORS SHALL BE BY WATTSOPPER, LUTRON, LEVITON, SENSOR SWITCH, HUBBELL, OR APPROVED EQUAL... 5. CIRCUIT BREAKERS SHALL BE MOLDED-CASE, THERMAL MAGNETIC TYPE WITH QUICK-MAKE, QUICK-BREAK MECHANISM... 6. ALL WIRE, CONNECTORS, TERMINALS, AND LUGS SHALL BE PROVIDED BY THE ELECTRICAL CONTRACTOR... 7. THE INSULATION TYPE FOR INTERIOR WIRING SHALL BE DUAL RATED THIN/THERM OR XHHW... 8. CABLES, RACEWAYS, OR BOXES, INSTALLED IN EXPOSED OR CONCEALED LOCATIONS UNDER METAL-CORRUGATED SHEET ROOF DECKING... 9. THE ELECTRICAL CONTRACTOR SHALL PROVIDE ALL OUTLET, JUNCTION, PULL BOXES, FITTINGS, AND SUPPORTS.

- 8. JOINTS IN SOLID CONDUCTORS SHALL BE SPLICED USING IDEAL "WIRE NUTS", "3M "SCOTCH LOCK", OR TAB "PIGGY" CONNECTORS... 9. ALL LUMINAIRES SHALL BE LISTED... 10. ALL CONDUIT, FITTINGS, COUPLINGS, AND SUPPORTS SHALL BE PROVIDED BY THE ELECTRICAL CONTRACTOR... 11. EMT SHALL BE MANUFACTURED IN ACCORDANCE WITH AMERICAN NATIONAL STANDARDS INSTITUTE-AMERICAN NATIONAL STANDARD FOR STEEL ELECTRICAL METALLIC TUBING (EMT), ANSI C80.3 AND UL 797... 12. METAL CONDUIT SHALL BE BY ALLED TUBING & CONDUIT, BECK MANUFACTURING, INC., OR WHELAN TUBE COMPANY... 13. ABANDONED CONDUIT AND BOXES SHALL HAVE ALL ELECTRICAL WIRING REMOVED COMPLETELY AND NOT JUST "MADE SAFE"... 14. WHERE CONDUCTORS ARE RUN IN PARALLEL, THE EC SHALL COMPLY WITH NEC 310.4... 15. ELECTRICAL CONTRACTOR SHALL INSTALL DISCONNECT SWITCHES IN SIGHT OF ALL HANDHELD EQUIPMENT AND APPLIANCES... 16. ELECTRICAL CONTRACTOR SHALL FIELD IDENTIFY ALL SWITCH BOARD, PANEL BOARDS, CONTROL PANELS, METER SOCKETS, ETC... 17. ELECTRICAL CONTRACTOR SHALL PROVIDE NAMEPLATES FOR IDENTIFICATION OF ALL EQUIPMENT, SWITCHES, PANELS... 18. TESTING WILL BE REQUIRED TO DETERMINE SATISFACTORY FIRST RESPONDER RADIO SIGNAL STRENGTH INSIDE EACH BUILDING ON SITE.

METHODS:

- 1. EC SHALL REVIEW THE MECHANICAL PLANS TO ESTABLISH POINTS OF CONNECTION AND THE EXTENT OF THE ELECTRICAL WORK... 2. ALL CIRCUIT BREAKERS FEEDING HVAC EQUIPMENT SHALL BE HACR BREAKERS... 3. COLOR CODE CONDUCTORS PER NEC... 4. ALL LIGHT FIXTURES SHALL BE SUPPORTED INDEPENDENTLY OF THE SUSPENDED CEILING... 5. MOUNT LIGHT SWITCHES AT 48 in AFF... 6. ELECTRICAL CONTRACTOR SHALL PROVIDE FIRE-STOPPING AT ALL ELECTRICAL PENETRATIONS OF RATED FLOORS AND WALLS... 7. ELECTRICAL CONTRACTOR SHALL PROVIDE GFCI RECEPTACLES IN KITCHENS, RESTROOMS, OUTDOORS, AND IN SHOP AREAS... 8. LOCATIONS AND HEIGHTS OF ALL WALL-MOUNTED DEVICES SHALL BE COORDINATED WITH THE ARCHITECT PRIOR TO INSTALLATION... 9. CONCEAL ALL CONDUIT EXCEPT IN MECHANICAL ROOMS... 10. CABLES, RACEWAYS, OR BOXES, INSTALLED IN EXPOSED OR CONCEALED LOCATIONS UNDER METAL-CORRUGATED SHEET ROOF DECKING... 11. THE ELECTRICAL CONTRACTOR SHALL PROVIDE ALL OUTLET, JUNCTION, PULL BOXES, FITTINGS, AND SUPPORTS.

- SHALL BE GALVANIZED STEEL TYPE BY APPLETON, STEEL CITY, OR RACO. EXTERIOR BOXES SHALL BE TYPE FS, WAPORITE BOXES SHALL BE TYPE GS... 12. ALL CONDUIT, BOXES, AND ELECTRICAL EQUIPMENT SHALL BE FIRMLY AND SECURELY FASTENED TO OR SUPPORTED FROM THE BUILDING STRUCTURAL MEMBERS OR EMBEDDED IN CONCRETE OR MASONRY... 13. ABANDONED CONDUIT AND BOXES SHALL HAVE ALL ELECTRICAL WIRING REMOVED COMPLETELY AND NOT JUST "MADE SAFE"... 14. WHERE CONDUCTORS ARE RUN IN PARALLEL, THE EC SHALL COMPLY WITH NEC 310.4... 15. ELECTRICAL CONTRACTOR SHALL INSTALL DISCONNECT SWITCHES IN SIGHT OF ALL HANDHELD EQUIPMENT AND APPLIANCES... 16. ELECTRICAL CONTRACTOR SHALL FIELD IDENTIFY ALL SWITCH BOARD, PANEL BOARDS, CONTROL PANELS, METER SOCKETS, ETC... 17. ELECTRICAL CONTRACTOR SHALL PROVIDE NAMEPLATES FOR IDENTIFICATION OF ALL EQUIPMENT, SWITCHES, PANELS... 18. TESTING WILL BE REQUIRED TO DETERMINE SATISFACTORY FIRST RESPONDER RADIO SIGNAL STRENGTH INSIDE EACH BUILDING ON SITE.


- 1. FIXTURE SHALL HAVE BATTERY BACKUP FOR 90 MINUTE ILLUMINATION. 2. OR EQUAL BY COOPER, PHILIPS, DAY-BRITE LIGHTING, GE, LITHONIA, OR OWNER APPROVED SELECTION. 3. PROVIDE WITH 90 MINUTE BATTERY BACKUP WHERE NOTED ON PLANS.

LIGHT FIXTURE SCHEDULE table with columns: MARK, DESCRIPTION, LOUVER/LENS, LAMPS (TYPE, QTY, CCT), VOLTAGE, MAX INPUT WATTAGE, MOUNTING, REMARKS, MFG, MODEL.


- 1. FIXTURE SHALL HAVE BATTERY BACKUP FOR 90 MINUTE ILLUMINATION. 2. OR EQUAL BY COOPER, PHILIPS, DAY-BRITE LIGHTING, GE, LITHONIA, OR OWNER APPROVED SELECTION. 3. PROVIDE WITH 90 MINUTE BATTERY BACKUP WHERE NOTED ON PLANS.

ELECTRICAL DESIGNER'S STATEMENT table with sections: ELECTRICAL SYSTEM AND EQUIPMENT METHOD OF COMPLIANCE, LIGHTING SCHEDULE, OCCUPANCY, UNOCCUPIED STORAGE, EQUIPMENT SCHEDULES WITH MOTORS.


FOR THE ADDITIONAL PRESCRIPTIVE REQUIREMENT REQUIRED BY C406 OF 2018 NORTH CAROLINA ENERGY CONSERVATION CODE, WE ARE CHOOSING C406.3 - REDUCED LIGHTING POWER DENSITY. 30700 W SPECIFIED <= 99258 W (110287 W ALLOWED X 90%)



GROUNDING DETAIL-NO SCALE




ELECTRICAL SCHEDULES AND KEY PLAN: NO SCALE



DESIGN FOR: ERWIN PLANT RENOVATIONS BUILDINGS 7, 8 & 9 ERWIN, NC

REVISIONS table with columns: NO., DESCRIPTION, DATE. ISSUED: table with columns: NO., DESCRIPTION, DATE. DRAWN BY: DBS, CHECKED BY: MIM/JAH, ELECTRICAL NOTES AND SCHEDULES, SHEET NO.: E1, PROJECT NO.: 230137




PANEL A									
CKT	LOAD	BKR	LOAD kVA	PH	LOAD kVA	BKR	LOAD	CKT	
1	BUILDING 9 LIGHTS	20/1	4.30	A	3.23	20/1	BUILDING 9 LIGHTS	2	
3	BUILDING 9 LIGHTS	20/1	3.23	B	4.30	20/1	BUILDING 9 LIGHTS	4	
5	SPACE		0.00	C	0.00		SPACE	6	
7	SPACE		0.00	A	0.00		SPACE	8	
9	SPACE		0.00	B	0.00		SPACE	10	
11	SPACE		0.00	C	0.00		SPACE	12	
13	SPACE		0.00	A	0.00		SPACE	14	
15	SPACE		0.00	B	0.00		SPACE	16	
17	SPACE		0.00	C	0.00		SPACE	18	
19	SPACE		0.00	A	0.00		SPACE	20	
21	SPACE		0.00	B	0.00		SPACE	22	
23	SPACE		0.00	C	0.00		SPACE	24	
25	SPACE		0.00	A	0.00		SPACE	26	
27	SPACE		0.00	B	0.00		SPACE	28	
29	SPACE		0.00	C	0.00		SPACE	30	
31	SPACE		0.00	A	0.00		SPACE	32	
33	SPACE		0.00	B	0.00		SPACE	34	
35	SPACE		0.00	C	0.00		SPACE	36	
37			14.20	A	7.90			38	
39	PANEL B	100/3	7.70	B	3.30	100/3	PANEL C	40	
41			7.70	C	0.00			42	
			kVA	PH	AMPS				
			29.6	A	107				
			18.5	B	67				
			7.7	C	28				

PANEL B									
CKT	LOAD	BKR	LOAD kVA	PH	LOAD kVA	BKR	LOAD	CKT	
1	BUILDING 8 LIGHTS	20/1	3.87	A	3.87	20/1	BUILDING 8 LIGHTS	2	
3	BUILDING 8 LIGHTS	20/1	3.87	B	3.87	20/1	BUILDING 8 LIGHTS	4	
5	BUILDING 8 LIGHTS	20/1	3.87	C	3.87	20/1	BUILDING 8 LIGHTS	6	
7	BUILDING 8 LIGHTS	20/1	3.87	A	2.58	20/1	BUILDING 8 LIGHTS	8	
9	SPACE		0.00	B	0.00		SPACE	10	
11	SPACE		0.00	C	0.00		SPACE	12	
13	SPACE		0.00	A	0.00		SPACE	14	
15	SPACE		0.00	B	0.00		SPACE	16	
17	SPACE		0.00	C	0.00		SPACE	18	
19	SPACE		0.00	A	0.00		SPACE	20	
21	SPACE		0.00	B	0.00		SPACE	22	
23	SPACE		0.00	C	0.00		SPACE	24	
25	SPACE		0.00	A	0.00		SPACE	26	
27	SPACE		0.00	B	0.00		SPACE	28	
29	SPACE		0.00	C	0.00		SPACE	30	
31	SPACE		0.00	A	0.00		SPACE	32	
33	SPACE		0.00	B	0.00		SPACE	34	
35	SPACE		0.00	C	0.00		SPACE	36	
37	SPACE		0.00	A	0.00		SPACE	38	
39	SPACE		0.00	B	0.00		SPACE	40	
41	SPACE		0.00	C	0.00		SPACE	42	
			kVA	PH	AMPS				
			14.2	A	51				
			7.7	B	28				
			7.7	C	28				

NEC ELECTRIC DEMAND SUMMARY 480Y/277V, 3P, 4W							
EQUIPMENT	DEMAND FACTOR	kVA			LOAD kVA	NEC REFERENCE	NOTES/CALCULATIONS
		A	B	C			
LIGHTING	100%	39.67	39.67	39.67	119.01	220.42	1ST 12.5kVA @ 100%, REMAINDER @ 50%
DEMAND kVA PER PHASE		39.67	39.67	39.67			
DEMAND AMPS PER PHASE		143	143	143			

THE CALCULATED LIGHTING LOAD EXCEEDS THE CONNECTED LIGHTING LOAD.



POWER KEY PLAN: NO SCALE