NEW PHOTOVOLTAIC SYSTEM 15.27 KW DC 219 BIRCH AVE, SPRING LAKE, NC 28390, USA

GENERAL NOTES

1.1.1 PROJECT NOTES:

1.1.2 THISPHOTOVOLTAIC (PV) SYSTEM SHALL COMPLY WITH THE NATIONAL ELECTRIC CODE (NEC) ARTICLE 690, ALL MANUFACTURERS'S LISTING AND INSTALLATION INSTRUCTIONS. AND THE RELEVANT CODES AS SPECIFIED BY THE AUTHORITY HAVING

JURISDICTION'S (AHJ) APPLICABLE CODES.

1.1.3 THE UTILITY INTERCONNECTION APPLICATION MUST BE APPROVED AND PV SYSTEM INSPECTED PRIOR TO PARALLEL OPERATION 1.1.4 GROUND FAULT DETECTION AND INTERRUPTION (GFDI) DEVICE IS INTEGRATED WITH THE MICROINVERTER IN ACCORDANCE WITH NEC 690.41(B)

1.1.5 ALL PV SYSTEM COMPONENTS; MODULES, UTILITY-INTERACTIVE INVERTERS, AND SOURCE CIRCUIT COMBINER BOXES ARE IDENTIFIED AND LISTED FOR USE IN PHOTOVOLTAIC SYSTEMS AS REQUIRED BY NEC 690.4: PV MODULES: UL1703, IEC61730, AND IEC61215, AND NFPA 70 CLASS C FIRE INVERTERS: UL 1741 CERTIFIED, IEEE 1547, 929, 519 COMBINER BOX(ES): UL 1703 OR UL 1741 ACCESSORY 1.1.6 MAX DC VOLTAGE CALCULATED USING MANUFACTURER PROVIDED

TEMP COEFFICIENT FOR VOC. IF UNAVAILABLE, MAX DC VOLTAGE CALCULATED ACCORDING TO NEC 690.7.

1.1.7 ALL INVERTERS, PHOTOVOLTAIC MODULES, PHOTOVOLTAIC PANELS, AND SOURCE CIRCUIT COMBINERS INTENDED FOR USE IN A PHOTOVOLTAIC POWER SYSTEM WILL BE IDENTIFIED AND LISTED FOR THE APPLICATIONPER 690.4 (D). SHALL BE INSTALLED ACCORDING TO ANY INSTRUCTIONS FROM LISTING OR LABELING [NEC 110.3]. 1.1.8 ALL SIGNAGE TO BE PLACED IN ACCORDANCE WITH LOCAL BUILDING CODE. IF EXPOSED TO SUNLIGHT. IT SHALL BE UV RESISTANT. ALL PLAQUES AND SIGNAGE WILL BE INSTALLED AS REQUIRED BY THE NEC AND AHJ.

1.2.1 SCOPE OF WORK:

1.2.2 PRIME CONTRACTOR IS RESPONSIBLE FOR THE DESIGN AND SPECIFICATIONS OF THE GRID-TIED PHOTOVOLTAIC SYSTEM RETROFIT. PRIME CONTRACTOR WILL BE RESPONSIBLE FOR COLLECTING EXISTING ONSITE REQUIREMENTS TO DESIGN, SPECIFY, AND INSTALL THE EXTERIOR ROOF-MOUNTED PORTION OF THE PHOTOVOLTAIC SYSTEMS DETAILED IN THIS DOCUMENT

1.3.1 WORK INCLUDES: 1.3.2 PV RACKING SYSTEM INSTALLATION - UNIRAC SOLAR 1.3.3 PV MODULE AND INVERTER INSTALLATION - LG ELECTRONICS LG355N1C-V5 / ENPHASE INVERTER 1.3.4 PV EQUIPMENT ROOF MOUNT 1.3.5 PV SYSTEM WIRING TO A ROOF-MOUNTED JUNCTION BOX 1.3.6 PV LOAD CENTERS (IF INCLUDED) 1.3.7 PV METERING/MONITORING (IF INCLUDED) 1.3.8 PV DISCONNECTS 1.3.9 PV GROUNDING ELECTRODE & BONDING TO (E) GEC 1.3.10 PV FINAL COMMISSIONING 1.3.11 (E) ELECTRICAL EQUIPMENT RETROFIT FOR PV 1.3.13 SIGNAGE PLACED IN ACCORDANCE WITH LOCAL BUILDING CODE

PROJECT INFORMATION

OWNER NAME: GLENDA CURRY

PROJECT MANAGER NAME: MATTHEW WEBB PHONE: 5052180838

CONTRACTOR NAME

MARC JONES CONSTRUCTION, LLC DBA SUNPRO SOLAR PHONE: 5052180838

11/25/2020 SCOPE OF WORK SYSTEM SIZE: STC:43 X 355W= 15.27 kW DC PTC: 43 x 332.8W = 14.31 kW DC (43) LG ELECTRONICS LG355N1C-V5 (43) ENPHASE IQ7PLUS-72-2-US

ATTACHMENT TYPE: ROOF MOUNT MSP UPGRADE: NO

AUTHORITIES HAVING JURISDICTION

BUILDING: HARNETT COUNTY ZONING: HARNETT COUNTY UTILITY: SOUTH RIVER

DESIGN SPECIFICATION

OCCUPANCY: CONSTRUCTION: SINGLE-FAMILY RESIDENTIAL ZONING: GROUND SNOW LOAD: 10 psf WIND EXPOSURE: C WIND SPEED: 118 mph

APPLICABLE CODES & STANDARDS

BUILDING: IBC 2015 IRC 2015 ELECTRICAL: NEC 2017 FIRE: IFC 2018

SHE T-001 CC G-001 NC A-101 Sľ A-102 EL A-103 AT ST A-104 LIN E-601 EL E-602 E-603 ΡL R-001 RE R-002 RE RE R-003 RE R-004 R-005 RE R-006 RE RE R-007 R-008 RE

SAT

Engin

with loading from the solar array and lag screw connections to the existing framing. The design of the racking system, connections,

all other nonstructural aspects of the design are by others. Electrical is by others, unless stamped by Dean Levorsen.

NC Firm License: COA #P-0742

SEA

049893

PRON

WRTH CARO

ind all other structure is by others. Mechanical, architectural, and

VSE Project Number: U3573.3125.201

651 W. GALENA PARK BLVD

Vector Structural Engineering has reviewed the

DRAPER, UTAH 84020

ERS

xisting structure

(801) 990-1775

<section-header><section-header><text><text><text><text><text><text></text></text></text></text></text></text></section-header></section-header>		SUNTR	22171 MCH RD MANDEVILLE, LA 70471 PHONE: 9152011490
Laurel Dr Bitty Mark	PROJECT NAME & ADDRESS	GLENDA CURRY	219 BIRCH AVE, SPRING LAKE, NC 28390, USA
ATELLITE VIEW		ס	219 BI LAKI
	Signature with Seal		
		DATE	
HEET INDEX COVER PAGE NOTES SITE PLAN ELECTRICAL PLAN ATTACHMENT PLAN STRUCTURAL PLAN LINE DIAGRAM ELECTRICAL CALCULATIONS PLACARD	REVISIONS	DESCRIPTION	
RESOURCE DOCUMENT RESOURCE DOCUMENT RESOURCE DOCUMENT		REV	
RESOURCE DOCUMENT RESOURCE DOCUMENT RESOURCE DOCUMENT RESOURCE DOCUMENT			ET TITLE ER PAGE
RESOURCE DOCUMENT RESOURCE DOCUMENT			11/03/2020 TSP
		EWED B	
	SHEET NUMBER		

2.1.1 SITE NOTES:

2.1.2 A LADDER WILL BE IN PLACE FOR INSPECTION IN COMPLIANCE WITH OSHA REGULATIONS.

2.1.3 THE PV MODULESARECONSIDERED NON-COMBUSTIBLE AND THIS SYSTEM IS A UTILITY INTERACTIVE SYSTEM WITH NO STORAGE BATTERIES.

2.1.4 THE SOLAR PV INSTALLATION WILL NOT OBSTRUCT ANY PLUMBING, MECHANICAL, OR BUILDING ROOF VENTS.

2.1.5 PROPERACCESS AND WORKING CLEARANCE AROUND EXISTING AND PROPOSED ELECTRICAL EQUIPMENT WILL BE PROVIDED AS PERSECTION NEC 110.26.

2.1.6 ROOF COVERINGS SHALL BE DESIGNED, INSTALLED, AND MAINTAINED IN ACCORDANCE WITH THIS CODE AND THE APPROVED MANUFACTURER'S INSTRUCTIONS SUCH THAT THE ROOF COVERING SERVES TO PROTECT THE BUILDING OR STRUCTURE.

2.2.1 EQUIPMENT LOCATIONS:

2.2.2 ALL EQUIPMENT SHALL MEET MINIMUM SETBACKS AS REQUIRED BY NEC 110.26.

2.2.3 WIRING SYSTEMS INSTALLED IN DIRECT SUNLIGHT MUST BE RATED FOR EXPECTED OPERATING TEMPERATURE AS SPECIFIED BY NEC 690.31 (A),(C) AND NEC TABLES 310.15 (B)(2)(A) AND 310.15 (B)(3)(C).

2.2.4 JUNCTION AND PULL BOXES PERMITTED INSTALLED UNDER PV MODULES ACCORDING TO NEC 690.34.

2.2.5 ADDITIONAL AC DISCONNECT(S) SHALL BE PROVIDED WHERE THE INVERTER IS NOT WITHIN SIGHT OF THE AC SERVICING DISCONNECT. 2.2.6 ALL EQUIPMENT SHALL BE INSTALLED ACCESSIBLE TO QUALIFIED PERSONNEL ACCORDING TO NEC APPLICABLE CODES.

2.2.7 ALL COMPONENTS ARE LISTED FOR THEIR PURPOSE AND RATED FOR OUTDOOR USAGE WHEN APPROPRIATE.

2.3.1 STRUCTURAL NOTES:

2.3.2 RACKING SYSTEM & PV ARRAY WILL BE INSTALLED ACCORDING TO CODE-COMPLIANT INSTALLATION MANUAL. TOP CLAMPS REQUIRE A DESIGNATED SPACE BETWEEN MODULES, AND RAILS MUSTALSO EXTEND A MINIMUM DISTANCE BEYOND EITHER EDGE OF THE ARRAY/SUBARRAY, ACCORDING TO RAI MANUFACTURER'S INSTRUCTIONS.

2.3.3 JUNCTION BOX WILL BE INSTALLED PER MANUFACTURERS' SPECIFICATIONS. IF ROOF-PENETRATING TYPE, IT SHALL BE FLASHED & SEALED PER LOCAL REQUIREMENTS.

2.3.4 ROOFTOP PENETRATIONS FOR PV RACEWAY WILLBE COMPLETED AND SEALED W/ APPROVED CHEMICAL SEALANT PER CODE BY A LICENSED CONTRACTOR.

2.3.5 ALL PV RELATED ROOF ATTACHMENTS TO BE SPACED NO GREATER THAN THE SPAN DISTANCE SPECIFIED BY THE RACKING MANUFACTURER. 2.3.6 WHEN POSSIBLE, ALL PV RELATED RACKING ATTACHMENTS WILL BE STAGGERED AMONGST THE ROOF FRAMING MEMBERS.

2.4.1 WIRING & CONDUIT NOTES:

2.4.2 ALL CONDUIT AND WIRE WILL BE LISTED AND APPROVED FOR THEIR PURPOSE. CONDUIT AND WIRE SPECIFICATIONS AREBASED ON MINIMUM CODE REQUIREMENTS AND ARE NOT MEANT TO LIMIT UP-SIZING.

2.4.3 CONDUCTORS SIZED ACCORDING TO NEC 690.8, NEC 690.7. 2.4.4 VOLTAGE DROP LIMITED TO 1.5%.

2.4.5 DC WIRING LIMITED TO MODULE FOOTPRINT. MICROINVERTER WIRING SYSTEMS SHALL BE LOCATED AND SECURED UNDER THE ARRAY W/ SUITABLE WIRING CLIPS.

2.4.6 AC CONDUCTORS COLORED OR MARKED AS FOLLOWS: PHASE A OR L1- BLACK PHASE B OR L2- RED, OR OTHER CONVENTION IF THREE PHASE PHASE C OR L3- BLUE, YELLOW, ORANGE**, OR OTHER CONVENTION NEUTRAL- WHITE OR GREY IN 4-WIRE DELTA CONNECTED SYSTEMS THE PHASE WITH HIGHER VOLTAGE TO BE MARKED ORANGE [NEC 110.15].

2.5.1 GROUNDING NOTES:

2.5.2 GROUNDING SYSTEM COMPONENTS SHALL BE LISTED FOR THEIR PURPOSE, AND GROUNDING DEVISES EXPOSED TO THE ELEMENTS SHALL BE RATED FOR SUCH USE.

2.5.3 PV EQUIPMENT SHALL BE GROUNDED ACCORDING TO NEC 690.43 AND MINIMUM NEC TABLE 250.122.

2.5.4 METAL PARTS OF MODULE FRAMES, MODULE RACKING, AND ENCLOSURES CONSIDERED GROUNDED IN ACCORD WITH 250.134 AND 250.136(A).

2.5.5 EQUIPMENT GROUNDING CONDUCTORS SHALLBE SIZED ACCORDING TO NEC 690.45 AND MICROINVERTER

MANUFACTORERS' INSTRUCTIONS.

2.5.6 EACH MODULE WILL BE GROUNDED USING WEEB GROUNDING CLIPS AS SHOWN IN MANUFACTURERDOCUMENTATION AND APPROVED BY THE AHJ. IF WEEBS ARE NOT USED, MODULE GROUNDING LUGS MUST BE INSTALLED AT THE SPECIFIED GROUNDING LUG HOLES PER THE MANUFACTURERS' INSTALLATION REQUIREMENTS.

2.5.7 THE GROUNDING CONNECTION TO A MODULE SHALL BE ARRANGED SUCH THAT THE REMOVAL OFA MODULE DOES NOT INTERRUPT A GROUNDING CONDUCTOR TO ANOTHER MODULE.

2.5.8 GROUNDING AND BONDING CONDUCTORS, IF INSULATED, SHALL BE COLORED GREEN OR MARKED GREEN IF #4 AWG OR LARGER [NEC 250.119]

2.5.9 THE GROUNDING ELECTRODE SYSTEM COMPLIES WITH NEC 690.47 AND NEC 250.50 THROUGH 250.106. IF EXISTING SYSTEM IS INACCESSIBLE, OR INADEQUATE, A GROUNDING ELECTRODE SYSTEM

PROVIDED ACCORDING TO NEC 250, NEC 690.47 AND AHJ. 2.5.10 GROUND-FAULT DETECTION SHALL COMPLY WITH NEC 690.41(B)(1) AND (2) TO REDUCE FIRE HAZARDS

2.6.1 DISCONNECTION AND OVER-CURRENT PROTECTION NOTES:


2.6.2 DISCONNECTING SWITCHES SHALL BE WIRED SUCH THAT WHENTHE SWITCH IS OPENED THE CONDUCTORS REMAINING ENERGIZED ARECONNECTED TO THE TERMINALS MARKED "LINE SIDE" (TYPICALLY THE UPPER TERMINALS). 2.6.3 DISCONNECTS TO BE ACCESSIBLE TO QUALIFIED UTILITY PERSONNEL, BE LOCKABLE, AND BE A VISIBLE-BREAK SWITCH 2.6.4 PV SYSTEM CIRCUITS INSTALLED ON OR IN BUILDINGS SHALL INCLUDE A RAPID SHUTDOWN FUNCTION TO REDUCE SHOCK HAZARD FOR EMERGENCY RESPONDERS IN ACCORDANCE WITH 690.12(A) THROUGH (D). 2.6.5 ALL OCPD RATINGS AND TYPES SPECIFIED ACCORDING TO NEC 690.8, 690.9, AND 240. 2.6.6 MICROINVERTER BRANCHES CONNECTED TO A SINGLE BREAKER OR GROUPED FUSES IN ACCORDANCE WITH NEC 110.3(B).

2.6.7 IF REQUIRED BY AHJ, SYSTEM WILL INCLUDE ARC-FAULT CIRCUIT PROTECTION ACCORDING TO NEC 690.11 AND UL1699B.

2.7.1 INTERCONNECTION NOTES:

2.7.2 LOAD-SIDE INTERCONNECTION SHALL BE IN ACCORDANCE WITH [NEC 705.12 (B)] 2.7.3 THE SUM OF THE UTILITY OCPD AND INVERTER CONTINUOUS OUTPUT MAY NOT EXCEED 120% OF BUSBAR RATING [NEC 705.12(D)(2)(3)]. 2.7.4 THE SUM OF 125 PERCENT OF THE POWER SOURCE(S) OUTPUT CIRCUIT CURRENT AND THE RATING OF THE OVERCURRENT DEVICE PROTECTING THE BUSBAR SHALL NOT EXCEED 120 PERCENT OF THE AMPACITY OF THE BUSBAR. PV DEDICATED BACKFEED BREAKERS MUST BE LOCATED OPPOSITE END OF THE BUS FROM THE UTILITY SOURCE OCPD [NEC 705.12(B)(2)(3)]. 2.7.5 AT MULTIPLE ELECTRIC POWER SOURCES OUTPUT COMBINER PANEL, TOTAL RATING OF ALL OVERCURRENT DEVICES SHALL NOT EXCEED AMPACITY OF BUSBAR. HOWEVER. THE COMBINED OVERCURRENT DEVICE MAY BE EXCLUDED ACCORDING TO NEC 705.12 (B)(2)(3)(C). 2.7.6 FEEDER TAP INTERCONECTION (LOADSIDE) ACCORDING TO NEC 705.12 (B)(2)(1) 2.7.7 SUPPLY SIDE TAP INTERCONNECTION ACCORDING TO NEC 705.12 (A) WITH SERVICE ENTRANCE CONDUCTORS IN ACCORDANCE WITH NEC 230.42 2.7.8BACKFEEDING BREAKER FOR ELECTRIC POWER SOURCES OUTPUT IS EXEMPT FROM ADDITIONAL FASTENING [NEC 705.12 (B)(5)].

SUNPR			22171 MCH RD		PHONE: 9152011490
PROJECT NAME & ADDRESS	GLENDA CURRY		219 BIRCH AVE, SPRING	LAKE, NC 28390, USA	
Signature with Seal					
	DATE				
REVISIONS	DESCRIPTION				
	REV				
	SHEET TITLE NOTES				
DRA	DRAWN DATE 11/03/2020 DRAWN BY TSP REVIEWED BY -				
	SHEET NUMBER G-001				



	SUNPR		22171 MCH RD		PHONE: 9152011490
PROJECT NAME & ADDRESS	PROJECT NAME & ADDRESS GLENDA CURRY		219 BIRCH AVE, SPRING	I AKE NC 28390 USA	
Signature with Seal					
	DATE				
REVISIONS	DESCRIPTION				
	REV		 -		
	sн SIT		TITL PLA		
	WN DA WN BY	TE	11/	03/2 TSF	
REV	REVIEWED BY - SHEET NUMBER A-101				


- CHIMNEY (ROOF OBSTRUCTION) - VENT, ATTIC FAN (ROOF OBSTRUCTION)

- SKYLIGHT (ROOF OBSTRUCTION)


- JUNCTION BOX


- PROPERTY LINE


- FIRE SETBACK



1			_				
ROOF SECTION(S)	ATTEN A			0474		06+	
ROOF 1 AZIMUTH - 284° MODULE - 24	IPR			22171 MCH RD ANDEVILLE, LA 7047 PHONE: 9152011490			
ROOF 2 AZIMUTH - 194° MODULE - 7		SUNPR		22171 MCH RD MANDEVILLE, LA 70471 PHONE: 9152011490			
ROOF 3 TILT - 43° AZIMUTH - 194° MODULE - 12	-	Л					
	PROJECT NAME & ADDRESS	GLENDA CURRY		219 BIRCH AVE, SPRING	LAKE, NC 28390, USA		
	Signature with Seal						
		DATE					
	REVISIONS	DESCRIPTION					
SETBACK ERTY LINE	E	SHI LECT	EET 1 RIC			AN	
FION BOX GHT (ROOF OBSTRUCTION)		WN DA	TE	11/	03/20 TSP	20	
NEY (ROOF OBSTRUCTION)	REV	IEWED SHEE	ET NU		- ER		
ATTIC FAN (ROOF OBSTRUCTION)		A	\-1(02			









TSP

-



SOLAR MODULE SPECIFICATIONS			
MANUFACTURER / MODEL #	LG ELECTRONICS LG355N1C-V5		
VMP	35.7V		
IMP	9.95A		
VOC	41.4V		
ISC	10.65A		
TEMP. COEFF. VOC	-0.27%/°C		
MODULE DIMENSION	66.4"L x 40"W x 1.57"D (In Inch)		

INVERTER SPECIFICATIONS			WIRE /CO
MANUFACTURER / MODEL #	ENPHASE IQ 7 PLUS MICROINVERTER	TAG	DESCRIPTION
MIN/MAX DC VOLT RATING	22V MIN/ 60V MAX		
MAX INPUT POWER	235W-440W	1	#12 THWN-2 & (1)#6 TH
NOMINAL AC VOLTAGE RATING	240V/ 211-264V	2	#4 THWN-2 & (1)#6 THW
MAX AC CURRENT	1.21A	3	#4 THWN-2 & (1)#6 THW
MAX MODULES PER STRING	13 (SINGLE PHASE)	4	(1)#6 BARE GROUND
MAX OUTPUT POWER	290 VA		



AMBIENT TEMPERATURE SPECS	3
RECORD LOW TEMP	-10°
AMBIENT TEMP (HIGH TEMP 2%)	36°
CONDUIT HEIGHT	0.5"
ROOF TOP TEMP	58°
CONDUCTOR TEMPERATURE RATE	90°
MODULE TEMPERATURE COEFFICIENT OF Voc	-0.27% /°C

PERCENT OF VALUES	NUMBER OF CURRENT CARRYING CONDUCTORS IN	EN
.80	4-6	
.70	7-9	
.50	10-20	
	*	

CALCULATIONS:

CURRENT CARRYING CONDUCTOR 1.

(A) **BEFORE IQ COMBINER PANEL**

AMBIENT TEMPERATURE - (36)°CNEC 310.15(B)(3)(c) **TEMPERATURE DERATE FACTOR - 0.91** ...NEC 310.15(B)(2)(a) **GROUPING FACTOR - 0.8...NEC 310.15(B)(3)(a)**

CONDUCTOR AMPACITY

= (INV O/P CURRENT) x 1.25 / A.T.F / G.FNEC 690.8(B) = [(11 x 1.21) x 1.25] / [0.91 x 0.8] = 22.85A SELECTED CONDUCTOR - #12 THWN-2 ...NEC 310.15(B)(16)

(B) AFTER IQ COMBINER PANEL **TEMPERATURE DERATE FACTOR - 0.91 GROUPING FACTOR - 1**

CONDUCTOR AMPACITY

- = (TOTAL INV O/P CURRENT) x 1.25 / 0.91/ 1 ... NEC 690.8(B)
- = [(43 x 1.21) x 1.25] / [0.91 x 1]


= 71.47 A

SELECTED CONDUCTOR - #4 THWN-2 ...NEC 310.15(B)(16)


2. PV OVER CURRENT PROTECTION ... NEC 690.9(B)

= TOTAL INVERTER O/P CURRENT x 1.25

= (43 x 1.21) x 1.25 = 65.04 A



	VONTR	22171 MCH RD MANDEVILLE, LA 70471 PHONE: 9152011490
PROJECT NAME & ADDRESS	GLENDA CURRY	219 BIRCH AVE, SPRING LAKE, NC 28390, USA
Signature with Seal		
	DATE	
REVISIONS	DESCRIPTION	
	REV	
SHEET TITLE ELECTRICAL CALCULATIONS DRAWN DATE 11/03/2020 DRAWN BY TSP REVIEWED BY - SHEET NUMBER E-602		



! CAUTION ! SOLAR POINT OF INTERCONNECTION


LABEL 9 AT UTILITY METER

! WARNING ! THE SERVICE METER IS ALSO SERVED BY A PHOTOVOLTAIC SYSTEM

LABEL 10 AT UTILITY METER

CAUTION

POWER TO THIS BUILDING IS ALSO SUPE FROM THE FOLLOWING SOURCES WIT DISCONNECTS LOCATED AS SHOWN



		SUNTR	22171 MCH RD	MANDEVILLE, LA 70471	PHONE: 9152011490
	PROJECT NAME & ADDRESS	GLENDA CURRY	219 BIRCH AVE. SPRING	LAKE, NC 28390, USA	
PLIED	Signature with Seal				
N:		DATE			
7	REVISIONS	DESCRIPTION			
PV ARRAY		SHE		Ē	
		PLA	CAR	DS	20
PV ARRAY	DRA	WN DAT WN BY IEWED E		/03/20 TSP -	20
UTILITY METER			T NUME		



THE NeON® 2 - 355W - THE PANEL OF THE FUTURE AVAILABLE TODAY

The LG NeON® 2 has seen many improvements, from longer warranties to lower degradation. This panel is ideal for homes seeking a visually pleasing solar panel and for roofs where space is tight or where future system expansions are considered e.g. to incorporate battery storage.

The LG NeON® 2 panels with their double sided cells and CELLO technology absorb light from the front and the back of the cell. This technology sets a new standard for innovation and was recognised with the 2015 Photovoltaic Innovation Award at the Intersolar Industry Event in Germany. LG also won the 2016 Intersolar award for our new NeON BiFacial range.



Great Visual Appearance

LG NeON® 2 panels have been designed with appearance in mind. Their black cells, black frames and thinner wire busbars give an aesthetically pleasing uniform black appearance. Your home deserves the LG NeON® 2.



More Power per Square Metre

LG NeON® 2's 355W are a similar physical size to many competing 300W panels. This means with the LG NeON® 2 355W you get 18% more electricity per square metre than a 300W panel. So you can install more kW of solar on your roof with the LG NeON® 2.

TO	25 Yea
11	The LG p
100.000	many.co

25 Years Product Warranty (Parts & Labour)

The LG product warranty is 15 years longer than many competitors standard 10 years. The Warranty is provided by LG Electronics Australia and New Zealand. The warranty includes replacement, labour and transport.



Improved 25 Year Performance Warranty

The initial degradation of the module has been improved from -3% to -2%, in the 1st year and the annual rate of degradation has fallen from -0.7%/year to -0.33%/ year thereafter. This brings an 90.08% warranted output after 25 years, compared to 80.2% for many competing panels

Made in Korea

Call LG Solar on 1300 152 179

www.lgenergy.com.au

LG355N1C-V5 | LG355N1C-V5

Cells	6 x 10
Cell Vendor	LG
Cell Type	Monocrystalline / N-type
Cell Dimensions	161.7 x 161 7 mm
≠ of Busbar	12 (Multi Wire Busbar)
Dimensions (L x W x H)	1686 x 1016 x 40 mm
Front Load (test)	5400 Pa
Rear Load (test)	4000 Pa
Weight	17.1 kg
Connector Type	Genuine MC4, IP68 (Male: PV-KST4) (Female: PV-KBT4)
Junction Box	IP68 with 3 bypass diodes
Length of Cables	2 x 1000 mm
Front cover	High transmission tempered glass
Frame	Anodised aluminum with protective matt black coating
Certifications and Warran	ty
	ISD 9001, ISO 14001, ISO 50001
	IEC 61215-1/-1-1/22016,
	IEC 61 720 1/2 2016 1/1 1702

ications and wantancy			
	ISD 9001, ISO 14001, ISO 50001		
	IEC 61215-1/-1-1/2.2015,		
cations	IEC 61 730-1/2 2016, UL1 703		
	OHSAS 18001		
r	Type 1 (UL 1703),		
e Fire Performance	Class C (UL 790, ULC/ORD C 1 703)		
t Warranty	25 Years		
t Warranty of Pmax rement Tolerance \pm 3%)	Linear Warranty ¹		

1) 1st year 98%, 2) After 1st year 0.33% annual degradation, 3) 90.08% for 25 years

Temperature Characteristics


Certifi

Module


Output


NMOT	42 ± 3 °C	
Pmax	+0.36 %/°C	
Voc	-0.27 %/°C	
Isc	0.03 %/℃	

Current - Voltage characteristics at various irradiance levels



Current – Voltage characteristics at various cell temperatures







LG Electronics Australia Pty Ltd Solar Business Group 2 Wonderland Drive, Eastern Creek, NSW 2766 Ph: 1300 152 179 E-Mail: solarsales@lge.com.au Web (benergy com.au

LS Electronics Inc. Pro Solar Business Division with Twin Building, Western Tower, 111; Dat 128, Yeoul-daerq, Yeongdeungpo-gu, Seoul, 07336, Korea Co www.lg.com/global/business au

Maximum Power Pmax (W) MPP Voltage Vmpp (V) MPP Current Impp (A) Open Circuit Voltage Voc (V) Short Circuit Current Isc (A) ² NVOT (Nominal Module Operating Temper wind speed 1 m/s, Spectrum AW 1 5

Dimensions (mm)

Electrical Properties (STC²)

Module Type Maximum Power Pmax (W)

MPP Voitage Vmpp (V) MPP Current Impp (A)

Module Efficiency (%)

Module Type

Open Circuit Voltage Voc (V) Short Circuit Current Isc (A)

Operating Temperature (°C) Maximum System Voltage (V)

Maximum Series Fuse Rating (A) Power Tolerance (%)


Electrical Properties (NMOT³)


350 W	355 W
350	355
35.3	35.7
9.92	9.95
41.3	41.4
10.61	10.65
20.4	20.7
-40 -	- +90
10	00
2	0
0-	+3

² STC (Standard Test Condition): Irradiance 10:00 W/m²; Module Temperature 25 °C, AM 1.5. The nameplate power output is measured and determined by LG Bectronics at its sole and absolute discretion.

1	350 W	355 W
	262	266
	33.2	335
	7.91	7.93
	38.9	39.0
	8.52	8.55

³ NMOT (Nominal Module Operating Temperature) Irradiance 800 W/m², ambient temperature 20 °C,





Copyright © 2019 LG Electronics. All rights reserved. Data Sheet Enphase Microinverters Region: AMERICAS

Enphase IQ 7 and IQ 7+ Microinverters

The high-powered smart grid-ready Enphase IQ 7 Micro[™] and Enphase IQ 7+ Micro[™] dramatically simplify the installation process while achieving the highest system efficiency.

Part of the Enphase IQ System, the IQ 7 and IQ 7+ Microinverters integrate with the Enphase IQ Envoy™, Enphase IQ Battery™, and the Enphase Enlighten™ monitoring and analysis software.

IQ Series Microinverters extend the reliability standards set forth by previous generations and undergo over a million hours of power-on testing, enabling Enphase to provide an industry-leading warranty of up to 25 years.



Easy to Install

- Lightweight and simple
- Faster installation with improved, lighter two-wire cabling
- Built-in rapid shutdown compliant (NEC 2014 & 2017)

Productive and Reliable

- · Optimized for high powered 60-cell and 72-cell* modules
- More than a million hours of testing
- · Class II double-insulated enclosure
- UL listed

Smart Grid Ready

- Complies with advanced grid support, voltage and frequency ride-through requirements
- Remotely updates to respond to changing grid requirements
- Configurable for varying grid profiles
- Meets CA Rule 21 (UL 1741-SA)
- * The IQ 7+ Micro is required to support 72-cell modules.



To learn more about Enphase offerings, visit enphase.com



Enphase IQ 7 and IQ 7+ Microinverters

INPUT DATA (DC)	107-60-2-US		107PLUS-72-2
Commonly used module pairings1	235 W - 350 W +		235 W - 440 W -
Module compatibility	60-cell PV modules only		60-cell and 72-c
Maximum input DC voltage	48 V		60 V
Peak power tracking voltage	27 V - 37 V		27 V - 45 V
Operating range	16 V - 48 V		16 V - 60 V
Min/Max start voltage	22 V / 48 V		22 V / 60 V
Max DC short circuit current (module Isc)	15 A		15 A
Overvoltage class DC port	н		Ш
DC port backfeed current	0.A		0.A
PV array configuration	1 x 1 ungrounde	d array; No additio	nal DC side protec
		ion requires max 20	
OUTPUT DATA (AC)	IQ 7 Microinve	erter	IQ 7+ Microin
Peak output power	250 VA		295 VA
Maximum continuous output power	240 VA		290 VA
Nominal (L-L) voltage/range ³	240 V / 211-264 V	208 V / 183-229 V	240 V / 211-264 V
Maximum continuous output current	1.0 A (240 V)	1.15 A (208 V)	1.21 A (240 V)
Nominal frequency	60 Hz		60 Hz
Extended frequency range	47 - 68 Hz		47 - 68 Hz
AC short circuit fault current over 3 cycles	5.8 Arms		5.8 Arms
Maximum units per 20 A (L-L) branch circuit ^a	16 (240 VAC)	13 (208 VAC)	13 (240 VAC)
Overvoltage class AC port	tii		111
AC port backfeed current	0 A 0		0 A
Power factor setting	1.0		1.0
Power factor (adjustable)	0.85 leading (0.85 lagging	0.85 leading (
EFFICIENCY	@240 V	@208 V	@240 V
Peak efficiency	97.6 %	97.6 %	97.5 %
CEC weighted efficiency	97.0 %	97.0 %	97.0 %
MECHANICAL DATA			
Ambient temperature range	-40°C to +65°C		
Relative humidity range	4% to 100% (cor	ndensing)	
Connector type (IQ7-60-2-US & IQ7PLUS-72-2-US)	MC4 (or Amphe	nol H4 UTX with ad	Iditional Q-DCC-5 a
Dimensions (WxHxD)	212 mm x 175 n	nm x 30.2 mm (with	out bracket)
Weight	1.08 kg (2.38 lb	Charles and the second s	
Cooling	Natural convect	ion - No fans	
Approved for wet locations	Yes		
Pollution degree	PD3		
Enclosure	Class II double-	insulated, corrosion	n resistant polyme
Environmental category / UV exposure rating	NEMA Type 6 /	outdoor	
FEATURES			
Communication	Power Line Con	nmunication (PLC)	
Monitoring	Enlighten Manager and MyEnlighten monitoring op Both options require installation of an Enphase IQ I		
Disconnecting means	The AC and DC connectors have been evaluated an disconnect required by NEC 690.		
Compliance	CA Rule 21 (UL 1741-SA) UL 62109-1, UL1741/IEEE1547, FCC Part 15 Class E CAN/CSA-C22.2 NO. 107.1-01 This product is UL Listed as PV Rapid Shut Down I NEC-2017 section 690.12 and C22.1-2015 Rule 64- and DC conductors, when installed according man		

No enforced DC/AC ratio. See the compatibility calculator at <u>https://enphase.com/en-us/support/module-compat</u>
 Nominal voltage range can be extended beyond nominal if required by the utility.
 S. Limits may vary. Refer to local requirements to define the number of microinverters per branch in your area.

3. Linhts may vary, Refer to local requirements to define the number of microinverters per branch in your area

To learn more about Enphase offerings, visit enphase.com

© 2019 Enphase Energy. All rights reserved. All trademarks or brands used are the property of Enphase Energy, Inc. 2019-3-26

2-US /+ -cell PV modules		SUNFR	22171 MCH RD	MANDEVILLE, LA 70471	PHONE: 9152011490
ction required; 208 V / 183-229 V 1.39 A (208 V) 11 (208 VAC) 0.85 lagging @208 V	PROJECT NAME & ADDRESS	GLENDA CURRY	219 BIRCH AVE. SPRING	LAKE, NC 28390, USA	
97.3 % 97.0 % adapter)	Signature with Seal				
eric enclosure lons. nvoy. I approved by UL for use as the load-break ICES-0003 Class B,	REVISIONS	DESCRIPTION			
tibility	DRA				
			T NUME		

Data Sheet Enphase Networking

Enphase **IQ Combiner 3** (X-IQ-AM1-240-3)

The Enphase IQ Combiner 3™ with Enphase IQ Envoy[™] consolidates interconnection equipment into a single enclosure and streamlines PV and storage installations by providing a consistent, pre-wired solution for residential applications. It offers up to four 2-pole input circuits and Eaton BR series busbar assembly.



To learn more about Enphase offerings, visit enphase.com

Smart

- Includes IQ Envoy for communication and control
- Flexible networking supports Wi-Fi, Ethernet, or cellular
- Optional AC receptacle available for PLC bridge
- · Provides production metering and optional consumption monitoring

Simple

- · Reduced size from previous combiner
- · Centered mounting brackets support single stud mounting
- · Supports back and side conduit entry
- · Up to four 2-pole branch circuits for 240 VAC plug-in breakers (not included)
- · 80 A total PV or storage branch circuits

ENPHASE.

Reliable

- Durable NRTL-certified NEMA type 3R enclosure
- Five-year warranty
- UL listed

CT-200-SPLIT Circuit Breakers


A BENERAL MANAGEMENT AND AN AND AN AND AN	
Production Metering CT	200 A solid core pre-installed and wired to IQ Envi
Max. total branch circuit breaker rating (input)	80A of distributed generation / 90A with IQ Envoy
Max. continuous current rating (input from PV)	64 A
Branch circuits (solar and/or storage)	Up to four 2-pole Eaton BR series Distributed Gen
Max. fuse/circuit rating (output)	90 A
Max. continuous current rating (output to grid)	65 A
Eaton BR series busbar rating	125 A
System voltage	120/240 VAC, 60 Hz
Rating	Continuous duty
ELECTRICAL SPECIFICATIONS	
XA-ENV-PCBA-3	Replacement IQ Envoy printed circuit board (PCB)
XA-PLUG-120-3	Accessory receptacle for Power Line Carrier in IQ
EPLC-01	Power line carrier (communication bridge pair), qu
BRK-10A-2-240 BRK-15A-2-240 BRK-20A-2P-240	Circuit breaker, 2 pole, 10A, Eaton BR210 Circuit breaker, 2 pole, 15A, Eaton BR215 Circuit breaker, 2 pole, 20A, Eaton BR215


	 Neutral and ground: 14 to 1/0 copper conducto Always follow local code requirements for conducto 		
Altitude	To 2000 meters (6,560 feet)		
INTERNET CONNECTION OPTIO	NS		
Integrated Wi-Fi	802.11b/g/n		
Ethernet	Optional, 802.3, Cat5E (or Cat 6) UTP Ethernet cable		
Cellular	Optional, CELLMODEM-01 (3G) or CELLMODEM-03 (not included)		
COMPLIANCE			
Compliance, Combiner	UL 1741 CAN/CSA C22.2 No. 107.1 47 CFR, Part 15, Class B, ICES 003 Production metering: ANSI C12.20 accuracy class 0		


Compliance, IQ Envoy




Enphase IQ Combiner 3 MODEL NUMBER IQ Combiner 3 X-IQ-AM1-240-3 ACCESSORIES and REPLACEMENT PARTS (no Enphase Mobile Connect [®]			SUNPR	MCH		
CELLMODEM-03 (4G / 12-year data plan) CELLMODEM-01 (3G / 5-year data plan) CELLMODEM-01 (4G based LTE-M / 5-year data plan) Consumption Monitoring* CT CT-200-SPLIT Circuit Breakers BRK-10A-2-240 BRK-10A-2-240 BRK-20A-2P-240 EPLC-01 XA-PLUG-120-3 XA-ENV-PCBA-3 ELECTRICAL SPECIFICATIONS Rating System voltage Eaton BR series busbar rating Max. continuous current rating (output to grid) Max. fuse/circuit rating (output) Branch circuits (solar and/or storage)	Plug and play industrial grade cellular modem with data plan for systems up to 60 microinverters. (Available in the US, Canada, Mexico, Puerto Rico, and the US Virgin Islands, where there is adequate cellular service in the installation area.) Split core current transformers enable whole home consumption metering (+/- 2.5%). Supports Eaton BR210, BR215, BR220, BR230, BR240, BR250, and BR260 circuit breakers. Circuit breaker, 2 pole, 10A, Eaton BR210 Circuit breaker, 2 pole, 15A, Eaton BR215 Circuit breaker, 2 pole, 20A, Eaton BR220 Power line carrier (communication bridge pair), quantity 2 Accessory receptacle for Power Line Carrier in IQ Combiner 3 (required for EPLC-01) Replacement IQ Envoy printed circuit board (PCB) for Combiner 3 Continuous duty 120/240 VAC, 60 Hz 125 A 65 A 90 A Up to four 2-pole Eaton BR series Distributed Generation (DG) breakers only (not included)	PROJECT NAME & ADDRESS	GLENDA CURRY	219 BIRCH AVE. SPRING	LAKE, NC 2839	
Max. continuous current rating (input from PV) Max. total branch circuit breaker rating (input) Production Metering CT MECHANICAL DATA Dimensions (WxHxD) Weight Ambient temperature range Cooling	64 A 80A of distributed generation / 90A with IQ Envoy breaker included 200 A solid core pre-installed and wired to IQ Envoy 49.5 x 37.5 x 16.8 cm (19.5" x 14.75" x 6.63"). Height is 21.06" (53.5 cm with mounting brackets). 7.5 kg (16.5 lbs) -40° C to +46° C (-40° to 115° F) Natural convection, plus heat shield	Signature with Seal				
Enclosure environmental rating Wire sizes	Outdoor, NRTL-certified, NEMA type 3R, polycarbonate construction 20 A to 50 A breaker inputs: 14 to 4 AWG copper conductors 60 A breaker branch input: 4 to 1/0 AWG copper conductors Main lug combined output: 10 to 2/0 AWG copper conductors Neutral and ground: 14 to 1/0 copper conductors Always follow local code requirements for conductor sizing.		DATE			
Altitude INTERNET CONNECTION OPTIONS Integrated Wi-Fi Ethernet Cellular COMPLIANCE Compliance, Combiner	To 2000 meters (6,560 feet) 802.11b/g/n Optional, 802.3, Cat5E (or Cat 6) UTP Ethernet cable (not included) Optional, CELLMODEM-01 (3G) or CELLMODEM-03 (4G) or CELLMODEM-M1 (4G based LTE-M) (not included) UL 1741 CAN/CSA C22.2 No. 107.1 47 CFR, Part 15, Class B, ICES 003 Production metering: ANSI C12.20 accuracy class 0.5 (PV production)	REVISIONS	DESCRIPTION			
Compliance, IQ Envoy	UL 60601-1/CANCSA 22.2 No. 61010-1		REV			
* Consumption monitoring is required for Enphase S To learn more about Enphase offerings, visit © 2018 Enphase Energy. All rights reserved. All trademarks or 2018-09-13		DRA	RES DO WN DA		CE NT /03/20 TSP -	20
			SHEE			=









	RT TABLE	PAR		
	DESCRIPTION		P/N	
	COMP KIT MILL, 20 PACK		004085M	
	COMP KIT DARK, 20 PACK	FLASHLOC	004085D	
SS LAG BOLT DM BONDED WASHER SS SERRATED T-BOLT				
Flashloc Base Mill or Dark	3 ³ / ₄ "			
57%"				
	PRODUCT LINE: SOLARN			
ALL		RAC	UNI	
RAWING	DRAWING TYPE: PART D		1411 BROADW	
			LBUQUERQUE, N	
C COMP KIT	DESCRIPTION: FLASHLO		PHONE: 505	







	γ.	4" BOLT LO		2 %/6"
	³ ∕k" Bolt Loo	CATION —		
08	PART #	TABLE		
P/N	DESCRIP	TION	LENGTH	
320132M	SM RAIL 132"	MILL	132"	
310132C	SM RAIL 132"	CLR	132"	
320168M	SM RAIL 168"	MILL	168"	
310168C	SM RAIL 168"	CLR	168"	
320168D	SM RAIL 168"	DRK	168"	
320208M	SM RAIL 208"	MILL	208"	
310208C	SM RAIL 208"	CLR	208"	
320240M	SM RAIL 240"	MILL	240"	
310240C	SM RAIL 240"	' CLR	240"	
310240D	SM RAIL 240"	DRK	240"	
1411 BROAD	WAY BLVD. NE	DRAWI	CT LINE: NG TYPE: PTION:	SOLARMOUNT PART DETAIL STANDARD RAIL
10 T 0 200 C 0 20	05.242.6411 NIRAC.COM	REVISIO	ON DATE:	9/11/2017

