# PHOTOVOLTAIC ROOF MOUNT SYS

22 MODULES-ROOF MOUNTED - 9.350 kW DC, 7.150 kW AC

483 RED CEDAR WY, FUQUAY-VARINA, NC 27526

#### **GENERAL NOTES PROJECT DATA** PROJECT 483 RED CEDAR WY, 1. ALL COMPONENTS ARE UL LISTED AND NEC CERTIFIED, WHERE WARRANTED. 1 ADDRESS FUQUAY-VARINA, NC 27526 2. THE SOLAR PV SYSTEM WILL BE INSTALLED IN ACCORDANCE WITH ARTICLE 690 OF THE NEC 2020 OWNER: SAMUEL LEE THE UTILITY INTERCONNECTION APPLICATION MUST BE APPROVED AND PV SYSTEM INSPECTED PRIOR TO PARALLEL 3. OPERATION. 080653000773 PARCEL ID: 4. ALL CONDUCTORS OF A CIRCUIT, INCLUDING THE EGC, MUST BE INSTALLED IN THE SAME RACEWAY, OR CABLE, OR 48 OTHERWISE RUN WITH THE PV ARRAY CIRCUIT CONDUCTORS WHEN THEY LEAVE THE VICINITY OF THE PV ARRAY. Fι ESR DESIGNER: WHERE METALLIC CONDUIT CONTAINING DC CONDUCTORS IS USED INSIDE THE BUILDING. IT SHALL BE IDENTIFIED AS 5 275 "CAUTION: SOLAR CIRCUIT" EVERY 10FT. SCOPE: 9.350 KW DC ROOF MOUNT SOLAR PV 6 HEIGHT OF THE AC DISCONNECT SHALL NOT EXCEED 6'-7" PER NEC CODE 240.24. SYSTEM WITH 22 JINKO SOLAR: JKM425N-54HL4-B 7 A GROUNDING ELECTRODE SYSTEM IN ACCORDANCE WITH NEC 2020 690.47 AND 250.50 THROUGH 60 AND 250-166 SHALL BE 425W MONO MODULES WITH PROVIDED. PER NEC GROUNDING ELECTRODE SYSTEM OF EXISTING BUILDING MAY BE USED AND BONDED TO THE SERVICE 22 ENPHASE IQ8M-72-M-US (325W) ENTRANCE. IF EXISTING SYSTEM IS INACCESSIBLE OR INADEQUATE A SUPPLEMENTAL GROUNDING ELECTRODE WILL BE USED AT THE INVERTER LOCATION CONSISTING OF A UL LISTED 8 FT. GROUND ROD WITH ACORN CLAMP. GROUNDING ELECTRODE MICROINVERTERS CONDUCTORS SHALL BE NO LESS THAN #8 AWG AND NO LARGER THAN #6 AWG COPPER AND BONDED TO THE EXISTING HC GROUNDING ELECTRODE TO PROVIDE FOR A COMPLETE SYSTEM. AUTHORITIES HAVING JURISDICTION: 8. PHOTOVOLTAIC MODULES ARE TO BE CONSIDERED NON-COMBUSTIBLE. **BUILDING : HARNETT COUNTY** ZONING : HARNETT COUNTY 9. PHOTOVOLTAIC INSTALLATION WILL NOT OBSTRUCT ANY PLUMBING. MECHANICAL, OR BUILDING ROOF VENTS UTILITY : DUKE ENERGY 10. ALL WIRING MUST BE PROPERLY SUPPORTED BY DEVICES OR MECHANICAL MEANS DESIGNED AND LISTED FOR SUCH USE. WIRING MUST BE PERMANENTLY AND COMPLETELY HELD OFF THE ROOF SURFACE. SHEET INDEX 11. ALL SINAGE TO BE PLACED IN ACCORDANCE WITH THE LOCAL BUILDING CODE. IF EXPOSED TO SUNLIGHT, IT SHALL BE UV PV-1 COVER SHEET RESISTANT, ALL PLAQUES AND SINAGE WILL BE INSTALLED AS REQUIRED BY THE NEC AND AHJ. PV-2 PLOT PLAN WITH ROOF PLAN 12. MICROINVERTERS USED IN UNGROUNDED SYSTEM SHALL BE UL 1741 LISTED. PV-3 **ROOF PLAN & MODULES** PV-4 ELECTRICAL PLAN 13. THE INSTALLATION OF EQUIPMENT AND ALL ASSOCIATED WIRING AND INTERCONNECTION SHALL BE PERFORMED ONLY BY PV-5 ATTACHMENT DETAIL QUALIFIED PERSONS [NEC 690.4(C)] PV-6 ELECTRICAL LINE DIAGRAM 14. ALL OUTDOOR EQUIPMENT SHALL BE NEMA 3R RATED (OR BETTER), INCLUDING ALL ROOF MOUNTED TRANSITION BOXES AND PV-7 WIRING CALCULATION SWITCHES PV-8 LABELS PV-9 MICROINVERTER CHART 15. ALL EQUIPMENT SHALL BE PROPERLY GROUNDED AND BONDED IN ACCORDANCE WITH NEC ARTICLE 250. PV-10+ EQUIPMENT SPECIFICATIONS 16. SYSTEM GROUNDING SHALL BE IN ACCORDANCE WITH NEC 690.41. 17. PV SYSTEM CIRCUITS INSTALLED ON OR IN BUILDINGS SHALL INCLUDE A RAPID SHUTDOWN FUNCTION IN ACCORDANCE WITH NEC 690.12 CODE 18. DISCONNECTING MEANS SHALL BE LOCATED IN A VISIBLE, READILY ACCESSIBLE LOCATION WITHIN THE PV SYSTEM EQUIPMENT OR A MAXIMUM OF 10 FEET AWAY FROM THE SYSTEM [NEC 690.13(A)] PROJECT TO COM 19. ALL WIRING METHODS SHALL BE IN ACCORDANCE WITH NEC 690.31 2020 NATIONAL E 20. WORK CLEARANCES AROUND ELECTRICAL EQUIPMENT WILL BE MAINTAINED PER NEC 110.26(A)(1), 110.26(A)(2) AND 110.26(A)(3). 2018 INTERNATIO 2018 INTERNATIO 21. ROOF MOUNTED PHOTOVOLTAIC PANELS AND MODULES SHALL BE TESTED. LISTED & IDENTIFIED IN ACCORDANCE WITH 2018 INTERNATIO UL1703 2018 INTERNATIO 22. ELECTRICAL CONTRACTOR TO PROVIDE CONDUIT EXPANSION JOINTS AND ANCHOR CONDUIT RUNS AS REQUIRED PER NEC.

07/01/2025

/A\

TEM	EMPWR 1007 JOHNI BLVD SI CHARLI SC 2 TEL: 854- EMAIL : info@e	LAR SOLAR NIE DODD: JITE 111 ESTON, 9464 999-4837 mpwrsolar	R s .com		
ICINITY MAP	REVIS DESCRIPTION REVISION	DATE 06/24/2025	REV A		
3 Red Cedar Wy, Iquay Varina, NC 526, United States	AND	A ROLIN SION 220 VEER IONES			
DUSE PHOTO	DATE:06	///////// RAL ONL' 2025	Y		
REFERENCES	PROJECT NAW SAMUEL LEE RESIDENCE	483 RED CEDAR WY, FUQUAY-VARINA,NC 27526	ESS		
	DRAW	VN BY SR			
LECTRICAL CODE (NEC) NAL FIRE CODE (IFC) NAL RESIDENTIAL CODE (IRC)	SHEET COVEF	NAME	т		
TRACE BOILDING CODE (IBC) NAL ENERGY CONSERVATION CODE (IECC) TRACE We were the funder code we were the funder code	SHEET SIZE ANSI B 11" X 17" SHEET NUMBER				
		- 1			

# **PROJECT DESCRIPTION:**

22 x JINKO SOLAR: JKM425N-54HL4-B 425W MONO MODULES ROOF MOUNTED SOLAR PHOTOVOLTAIC MODULES DC SYSTEM SIZE: 9.350 kW DC AC SYSTEM SIZE: 7.150 kW AC

EQUIPMENT SUMMARY

22 JINKO SOLAR: JKM425N-54HL4-B 425W MONO MODULES 22 ENPHASE IQ8M-72-M-US (325W) MICROINVERTERS

ROOF ARRAY AREA #1:- 239.76 SQ FT. ROOF ARRAY AREA #2:- 199.80 SQ FT.

NOTE: VISIBLE, LOCKABLE, LABELED AC DISCONNECT LOCATED WITHIN 10' OF UTILITY METER



PROPERTY LINE R



EMPWR 1007 JOHNI BLVD SU CHARLI SC 2 TEL: 854- EMAIL : info@e	L A R SOLAR NIE DODD: JITE 111 ESTON, 9464 999-4837 mpwrsolar	S.							
	DATE	REV							
REVISION	06/24/2025	А							
MGINEER STRUCTURAL ONLY 06/26/2025									
DATE:06 PROJECT NAM	/23/2025 IE & ADDRI	ESS							
SAMUEL LEE RESIDENCE 483 RED CEDAR WY, UQUAY-VARINA,NC 27526									
DRAW	IN BY SR								
SHEET PLOT PL ROOF	AN WI PLAN	TH							
SHEE ANS 11" >	r size SI B K 17"								
SHEET	NUMBER -2								

/A\



					~~			
00	F DESC	RIPTIO	N		<u>}</u>			
		ASPHA	ASPHALT SHINGLE					
OF CH	AZIMUTH	TRUSS SIZE		TRUSS SPACING				
5°	148°	2"X4"		24"	{			
3°	328°	2"X4"		24"	{			
			Δ		,   }			
					{ {			
F LES	ARRAY AREA (Sq. Ft.)	ROOF AREA (Sq. Ft.)	С	AREA OVERED BY ARRAY (%)				
	239.76	677.68		35	}			
	199.80	770.99		26	1 {			
	439.56	1651.28		27	}			
V-54H	HL4-B 425	N						
25W)	ł							



JINKO SOLAR: JKM425N-54HL4-B





• • • • • • • • • • • • • • • • • • • •	$\frown$			
MATERIALS	] }			/R
DESCRIPTION KO SOLAR: JKM425N-54HL4-B 425W MONO		EMPWR 1007 JOHN	<b>SOLAR</b> NIE DODD	s
PHASE IQ8M-72-M-US (325W) MICROINVERTERS		BLVD SU CHARL	JITE 111 ESTON.	
ICTION BOXES		SC 2	9464	
NRIDGE XR-10 RAIL	3	EMAIL : info@e	empwrsolar	.com
ICES	}	REVIS	SIONS	
MODULE CLAMPS		DESCRIPTION	DATE	REV
CLAMPS / STOPPER SLEEVE	X	REVISION	06/24/2025	А
NRIDGE HALO ULTRAGRIP ATTACHMENTS	{			
	' }			
D INTO THE RAILS STS COUNTS.		[		
JS (325W) NEL (240V)	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~			
	}		1/23/2025	FSS
	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	SAMUEL LEE RESIDENCE	483 RED CEDAR WY, FUQUAY-VARINA,NC 27526	
		DRAV	VN BY SR	
LEGEND MSP - MAIN SERVICE PANEL		ELECT PL	RICAL AN	_
CB     - COMBINER BOX       ACD     - AC DISCONNECT       UM     - UTILITY METER		SHEE ANS 11" )	T SIZE SI B K 17"	

JB - JUNCTION BOX - CONDUIT

SHEET NUMBER PV-4





#### DC SYSTEM SIZE: 9.350 kW DC AC SYSTEM SIZE: 7.150 kW AC

WET LOCATIONS AND UV PROTECTED

PV-6

ELECTRICAL LINE DIAGRAM

SCALE: NTS

#### **GROUNDING & GENERAL NOTES:**

1. PV GROUNDING ELECTRODE SYSTEM NEEDS TO BE INSTALLED IN ACCORDANCE WITH [NEC 690.43]

#### INTERCONNECTION NOTES:

1. INTERCONNECTION SIZING, LIMITATIONS AND COMPLIANCE DETERMINED IN ACCORDANCE WITH [NEC 705.12], AND [NEC 2. GROUND FAULT PROTECTION IN ACCORDANCE WITH [NE

3. ALL EQUIPMENT TO BE RATED FOR BACKFEEDING. 4. PV BREAKER TO BE POSITIONED AT THE OPPOSITE END O BUSBAR RELATIVE TO THE MAIN BREAKER.

1. DISCONNECTING SWITCHES SHALL BE WIRED SUCH THAT THE SWITCH IS OPENED THE CONDUCTORS REMAINING LIV CONNECTED TO THE TERMINALS MARKED "LINE SIDE" (TYPI THE UPPER TERMINALS)

2. AC DISCONNECT MUST BE ACCESSIBLE TO QUALIFIED UT PERSONNEL, BE LOCKABLE, AND BE A VISIBLE-BREAK SWIT

1.BOND EVERY OTHER RAIL WITH #6 BARE COPPER

#### **INSTALLER/ELECTRICIAN NOTE:**

EC IS TO MEASURE VOLTAGE BEFORE STARTING WORK. IF RESULT IS ANY OTHER VOLTAGE MEASURED THAN 120/2 OBSERVED, DO NOT PROCEED. CONTACT ENGINEER

	QTY	C	CONDUCTOR INFORMATION	
$\bigcirc$	(6)	CU #12AWG -	ENPHASE ENGAGE CABLE (L1 &L2 NO NEUTRAL)	
U	(1)	CU #6AWG -	BARE COPPER IN FREE AIR	1
$\bigcirc$	(6)	CU #10AWG -	THWN-2 (L1,L2)	
Ý	(1)	CU #10AWG -	THWN-2 GND	[=
$\bigcirc$	(3)	CU #8AWG -	THWN-2 (L1,L2,&N)	Ļ
ु	(1)	CU #10AWG -	THWN-2 GND	۱E
(4)	(3)	CU #8AWG -	THWN-2 (L1,L2 & N)	Ē
$\sim$	(1)	CU #10AWG -	THWN-2 GND	

ID COMPLIAN .12], AND [NE NCE WITH [N EDING. POSITE END ED SUCH THA EMAINING LI VE SIDE" (TYI QUALIFIED L E-BREAK SWI PPER FING WORK. ED THAN 120 IGINEER	NCE EC 690.59]. EC 215.9], D OF THE AT WHEN VE ARE PICALLY JTILITY ITCH D/240V IS TO UTILITY M BI-DIRECTI UTILITY ME 120/240V, 1	$\int_{L_{L_{L_{L_{L_{L_{L_{L_{L_{L_{L_{L_{L_$	EMPWR SOLAR 1007 JOHNNIE DODI BLVD SUITE 1111 CHARLESTON, SC 29464 TEL: 854-999-4837 EMAIL : info@empwrsola REVISIONS DESCRIPTION DATE REVISION 06/24/2025	
G G G G G G G G G G C G G C C C C C C C	(E) MAIN BF HOUSE 240 (E) MAIN SE PANEL, SQU 200A RATED LOAD SIDE INTERCONN MAIN SERVI BACK FEED REF 2020 NEC 7	REAKER TO V, 200A/2P RVICE JARE D D, 240V JECTION AT CE PANEL D BREAKER 705.12(B)(3)(2)	DATE:06/23/2025 PROJECT NAME & ADDI RESIDENCE 483 RED CEDAR WY, ABINA NC 2755 1011AY-VARINA NC 2755 1011AY-VAX	RESS
		}	DRAWN BY ESR	
			SHEET NAME ELECTRICAL L DIAGRAM	INE
AL)	N/A			=
	EMT OR LFMC IN ATTIC	3/4"	ANSI B	
	EMT	3/4"	SHEET NUMBER	$\dashv$
)	EMT	3/4"	PV-6	
	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	······		

INVERTER SPECIFICATIONS							
MANUFACTURER / MODEL #	ENPHASE IQ8M-72-M-US (325W) MICROINVERTS						
MIN/MAX DC VOLT RATING	25V MIN/ 58V MAX						
MAX INPUT POWER	260W-460W						
NOMINAL AC VOLTAGE RATING	240V/ 211-264V						
MAX AC CURRENT	1.35A						
MAX MODULES PER CIRCUIT	11 (SINGLE PHASE)						
MAX OUTPUT POWER	325 VA						

SOLA	R MODULE SPECIFICATIONS	]	AM	BIENT TEMPERATURE SPECS	5		
MANUFACTURER / MODEL #	JINKO SOLAR: JKM425N-54HI 4-B 425W MODULE		RECORD LOW T	EMP		-8°	
\ (A 4 D		-	AMBIENT TEMP	(HIGH TEMP 2%)	3	38°	
VMP	VMP 32.37V		CONDUCTOR TEMPERATURE RATE			90°	
IMP	13.13A				0.050//90		
VOC	38.95V			RATURE COEFFICIENT OF Voc	-0.25%/		
ISC	13.58A	]	PERCENT OF	NUMBER OF CURRENT			
TEMP. COEFF. VOC	-0.25%/°C		VALUES	CARRYING CONDUCTORS IN I	EMT		
MODULE DIMENSION	67.79"L x 44.65"W x 1.38"D (In Inch)	1	.80	4-6			
		-	.70	7-9			

.50

	AC FEEDER CALCULATIONS																							
CIRCUIT ORIGIN		VOLTAGE (V)	FULL LOAD AMPS "FLA" (A)	FLA*1.25 (A)	OCPD SIZE (A)	NEUTRAL SIZE	GROUND SIZE	CONDUCTOR SIZE	CT WIRE SIZE (Twisted per pair)	CT WIRES IN RACEWAY	75°C AMPACITY (A)	AMPACITY CHECK #1	AMBIENT TEMP. (°C)	TOTAL CC CONDUCTORS IN RACEWAY	90°C AMPACITY (A)	DERATION FACTOR FOR AMBIENT TEMPERATURE NE 310.15(B){1)	C DERATION FACTOR FOR CONDUCTORS PER RACEWAY NEC 310.15(B)(1)	90°C AMPACITY DERATED (A)	AMPACITY CHECK #2	FEEDER LENGTH (FEET)	CONDUCTOR RESISTANCE (OHM/KFT)	VOLTAGE DROP AT FLA (%)	CONDUIT SIZE	CONDUIT FILL (%)
CIRCUIT 1	JUNCTION BOX	240	14.85	18.5625	20	N/A	BARE COPPER #6 AWG	6 CU #12 AWG	N/A	0	25	PASS	38	2	30	0.91	1	27.3	PASS			0.62	N/A	#N/A
CIRCUIT 2	JUNCTION BOX	240	14.85	18.5625	20	N/A	BARE COPPER #6 AWG	6 CU #12 AWG	N/A	0	25	PASS	38	2	30	0.91	1	27.3	PASS		<u> </u>	0.62	N/A	#N/A
JUNCTION BOX	COMBINER BOX	240	14.85	18.5625	20	N/A	CU #10 AWG	CU #10 AWG	N/A	0	35	PASS	38	4	40	0.91	0.8	29.12	PASS	35	1.24	0.537	3/4" EMT	19.79%
COMBINER BOX	AC DISCONNECT	240	29.7	37.125	40	CU #8 AWG	CU #10 AWG	CU #8 AWG	CU #18 AWG	2	50	PASS	38	2	55	0.91	1	50.05	PASS	5	0.778	0.096	3/4" EMT	29.21%
AC DISCONNECT	POI	240	29.7	37.125	40	CU #8 AWG	CU #10 AWG	CU #8 AWG	CU #18 AWG	2	50	PASS	38	2	55	0.91	1	50.05	PASS	5	0.778	0.096	3/4" EMT	29.21%
																				Circuit 1 Circuit 2	Voltage Drop Voltage Drop	1.350 1.350	]	

#### ELECTRICAL NOTES

- 1. ALL EQUIPMENT TO BE LISTED BY UL OR OTHER NRTL, AND LABELED FOR ITS APPLICATION.
- 2. ALL CONDUCTORS SHALL BE RATED UPTO 600V FOR RESIDENTIAL AND 1000V FOR COMMERCIAL AND 90 DEGREE C WET ENVIRONMENT.
- 3. WIRING, CONDUIT, AND RACEWAYS MOUNTED ON ROOFTOPS SHALL BE ROUTED DIRECTLY TO, AND LOCATED AS CLOSE AS POSSIBLE TO THE NEAREST RIDGE, HIP, OR VALLEY.
- 4. WORKING CLEARANCES AROUND ALL NEW AND EXISTING ELECTRICAL EQUIPMENT SHALL COMPLY WITH NEC 110.26.
- 5. DRAWINGS INDICATE THE GENERAL ARRANGEMENT OF SYSTEMS. CONTRACTOR SHALL FURNISH ALL NECESSARY OUTLETS, SUPPORTS, FITTINGS AND ACCESSORIES TO FULFILL APPLICABLE CODES AND STANDARDS.
- 6. WHERE SIZES OF JUNCTION BOX, RACEWAYS, AND CONDUITS ARE NOT SPECIFIED, THE CONTRACTOR SHALL SIZE THEM ACCORDINGLY.
- 7. ALL WIRE TERMINATIONS SHALL BE APPROPRIATELY LABELED AND READILY VISIBLE.
- 8. MODULE GROUNDING CLIPS TO BE INSTALLED BETWEEN MODULE FRAME AND MODULE SUPPORT RAIL, PER THE GROUNDING CLIP MANUFACTURER'S INSTRUCTION.
- 9. MODULE SUPPORT RAIL TO BE BONDED TO CONTINUOUS COPPER G.E.C. VIA WEEB LUG OR ILSCO GBL-4DBT LAY-IN LUG.
- 10. TEMPERATURE RATINGS OF ALL CONDUCTORS, TERMINATIONS, BREAKERS, OR OTHER DEVICES ASSOCIATED WITH THE SOLAR PV SYSTEM SHALL BE RATED FOR AT LEAST 75 DEGREE C.

_										
	EN S O EMPWR 1007 JOHN BLVD SL	LAR SOLAR NIE DODD	<b>/R</b> s							
	CHARLESTON, SC 29464									
	TEL: 854-999-4837 EMAIL : info@empwrsolar.com									
	REVISIONS									
	DESCRIPTION	DATE	REV							
	REVISION	06/24/2025	А							
	DATE:06	/23/2025								
	PROJECT NAM	IE & ADDRI	ESS							
		9								
		ر, 752								
	ШШ	S N S								
		, AR								
		INA D								
		ARI								
	₩ N S U	E S								
	S ⊾	33 F JA								
1		₽ NOL								
		Ц								
	DRAV	VN BY	Ħ							
	E\$	SR								
	SHEET	NAME	$\dashv$							
	WIR	ING								
	CALCUL	ATION	s							
	SHEE	T SIZE	$\dashv$							
	ANS	SI B								
	11">	K 17"								
	SHEET N	NUMBER	╡							
	עם <u>ו</u>	/_7	1							

10-20

# CAUTION: AUTHORIZED SOLAR PERSONNEL ONLY!

LABEL-1: LABEL LOCATION: AC DISCONNECT

# **WARNING**

#### ELECTRIC SHOCK HAZARD

TERMINALS ON THE LINE AND LOAD SIDES MAY BE ENERGIZED IN THE OPEN POSITION

LABEL- 2: <u>LABEL LOCATION:</u> AC DISCONNECT COMBINER MAIN SERVICE PANEL SUBPANEL MAIN SERVICE DISCONNECT CODE REF: NEC 705.20(7) & 690.13(B)

MARNING DUAL POWER SOURCE SECOND SOURCE IS PHOTOVOLTAIC SYSTEM

LABEL- 3: <u>LABEL LOCATION:</u> UTILITY METER MAIN SERVICE PANEL SUBPANEL CODE REF: NEC 705.30(C) & NEC 690.59

# 

TURN OFF PHOTOVOLTAIC AC DISCONNECT PRIOR TO WORKING INSIDE PANEL

LABEL- 4: <u>LABEL LOCATION:</u> MAIN SERVICE PANEL SUBPANEL MAIN SERVICE DISCONNECT COMBINER CODE REF: NEC 110.27(C) & OSHA 1910.145(f)(7)



POWER SOURCE OUTPUT CONNECTION. DO NOT RELOCATE THIS OVERCURRENT DEVICE

LABEL- 5: LABEL LOCATION:

MAIN SERVICE PANEL (ONLY IF SOLAR IS BACK-FED) SUBPANEL (ONLY IF SOLAR IS BACK-FED) CODE REF: NEC 705.12 (B)(2)

# SOLAR PV SYSTEM EQUIPPED WITH RAPID SHUTDOWN

"OFF" POSITION TO SHUT DOWN PV SYSTEM AND REDUCE SHOCK HAZARD IN THE ARRAY

LABEL- 6: LABEL LOCATION: AC DISCONNECT

CODE REF: IFC 605.11.3.1(1) & 690.12(D)

# RAPID SHUTDOWN SWITCH FOR SOLAR PV SYSTEM

LABEL- 7:

LABEL LOCATION: AC DISCONNECT CODE REF: NEC 690.12(D)(2)

PHOTOVOLTAIC AC DISCONNECT	
IOMINAL OPERATING AC VOLATGE	240 V
ATED AC OUTPUT CURRENT	29.70 A

LABEL- 8: <u>LABEL LOCATION:</u> MAIN SERVICE PANEL SUBPANEL AC DISCONNECT CODE REF: NEC 690.54

EMPWR SOLAR EMPWR SOLAR 1007 JOHNNIE DODDS BLVD SUITE 111 CHARLESTON, SC 29464 TEL: 854-999-4837 EMAIL: info@mmurgalac.com										
DESCRIPTION	DATE	REV								
REVISION	06/24/2025	А								
DATE:06	5/23/2025 1E & ADDRI	ESS								
SAMUEL LEE RESIDENCE	483 RED CEDAR WY, FUQUAY-VARINA,NC 27526									
	VN BY SR									
LAB	ELS									
SHEE ANS 11" >	t size SI B K 17"									
SHEET										
	-ŏ									





# THE MOST DEPENDABLE SOLAR PRODUCT

# EAGLE<sup>®</sup> 54 G6R 420-440 WATT • N-TYPE TOPCON

Positive power tolerance of 0~+3%

• NYSE-listed since 2010, Bloomberg Tier 1 manufacturer

- Top performance in the strictest 3<sup>rd</sup> party labs
- Automated manufacturing utilizing artificial intelligence
- · Vertically integrated, tight controls on quality
- Premium solar factories in USA, Vietnam, and Malaysia

# **KEY FEATURES**

#### Superior Aesthetics

Black backsheet and black frame create ideal look for residential applications.



N-Type Technology N-type cells with Jinko's in-house TOPCon technology offers better performance and improved reliability.

#### Thick and Tough TOUGH FRAME GLAS

Fire Type 1 rated module engineered with a thick frame, 3.2mm front side glass, and thick backsheet for added durability.

Shade Tolerant

Twin array design allows continued performance even with shading by trees or debris.

#### Protected Against All Environments

Certified to withstand humidity, heat, rain, marine environments, wind, hailstorms, and packed snow.



25-year product and 30-year linear power warranty.

- IS09001:2015 Quality Standards
- IS014001:2015 Environmental Standards
- IEC61215, IEC61730 certified products
- Health & Safety Standards UL61730 certified products

ISO45001: 2018 Occupational

#### **BUILDING YOUR TRUST IN SOLAR. WWW.JINKOSOLAR.US**



## ENGINEERING DRAWINGS



MECHANICAL CHARACTERISTICS					
No. of Half Cells	108 (2 x 54)				
Dimensions	1722 × 1134 × 35mm (67.79 × 44.65 × 1.38 inch)				
Weight	21.0kg (46.3lbs)				
Front Glass	3.2mm, Anti-Reflection Coating High Transmission, Low Iron, Tempered Glass				
Frame	Anodized Aluminum Alloy				
Junction Box	IP68 Rated				
Output Cables	12 AWG, 1400mm (55.12in) or Customized Length				
Connector	Staubli MC4				
Fire Type	Type 1				
Pressure Rating	5400Pa (Snow) & 2400Pa (Wind)*				

#### **TEMPERATURE CHARACTERISTICS**



Temperature Coefficients of F Temperature Coefficients of V Temperature Coefficients of I Nominal Operating Cell Temp

Operating Temperature (°C)

#### **ELECTRICAL PERFORMANCE & TEMPERATURE DEPENDENCE** MAXIMUM RATINGS



# of Isc, Voc, Pmax

Temperature Dependence

Cell Temperature (°C)

## WARRANTY

25-year product and 30-year linear power warranty 1<sup>st</sup> year degradation not to exceed 1%, each subsequent year not to exceed 0.4%, minimum power at year 30 is 87.4% or greater.

#### FLECTRICAL CHARACTERISTICS

100									
JKM420N-	54HL4-B	JKM425N	1-54HL4-B	JKM430N	-54HL4-B	JKM435N	I-54HL4-B	JKM440N	I-54HL4-B
STC	NOCT	STC	NOCT	STC	NOCT	STC	NOCT	STC	NOCT
420Wp	316Wp	425Wp	320Wp	430Wp	323Wp	435Wp	327Wp	440Wp	331Wp
32.16V	29.95V	32.37V	30.19V	32.58V	30.30V	32.78V	30.50V	32.99V	30.73V
13.06A	10.55A	13.13A	10.60A	13.20A	10.66A	13.27A	10.72A	13.34A	10.77A
38.74V	36.80V	38.95V	37.00V	39.16V	37.20V	39.36V	37.39V	39.57V	37.59V
13.51A	10.91A	13.58A	10.96A	13.65A	11.02A	13.72A	11.08A	13.80A	11.14A
21.5	1%	21.	.76%	22.0	02%	22.	28%	22.	53%
🛛 Cell	Temperatu pient Temp	ure 25°C erature 2	ර ගංද ර	> AM = 1.5 > AM = 1.5	<u>⊸</u> w	ind Speed	1m/s		
	JKM420N- STC 420Wp 32.16V 13.06A 38.74V 13.51A 21.5 Cell Amb	JKM420N-54HL4-B STC NOCT 420Wp 316Wp 32.16V 29.95V 13.06A 10.55A 38.74V 36.80V 13.51A 10.91A 21.51% Cell Temperatu Ambient Temp	JKM420N-54HL4-B JKM425N STC NOCT STC 420Wp 316Wp 425Wp 32.16V 29.95V 32.37V 13.06A 10.55A 13.13A 38.74V 36.80V 38.95V 13.51A 10.91A 13.58A 21.51% 21 Cell Temperature 25°C Ambient Temperature 2	JKM420N-54HL4-B JKM425N-54HL4-B STC NOCT STC NOCT 420Wp 316Wp 425Wp 320Wp 32.16V 29.95V 32.37V 30.19V 13.06A 10.55A 13.13A 10.60A 38.74V 36.80V 38.95V 37.00V 13.51A 10.91A 13.58A 10.96A 21.51% 21.76% Cell Temperature 25°C C	JKM420N-54HL4-B         JKM425N-54HL4-B         JKM430N           STC         NOCT         STC         NOCT         STC           420Wp         316Wp         425Wp         320Wp         430Wp           32.16V         29.95V         32.37V         30.19V         32.58V           13.06A         10.55A         13.13A         10.60A         13.20A           38.74V         36.80V         38.95V         37.00V         39.16V           13.51A         10.91A         13.58A         10.96A         13.65A           21.51%         21.76%         22.0         21.76%         22.0	JKM420N-54HL4-B       JKM425N-54HL4-B       JKM430N-54HL4-B         STC       NOCT       STC       NOCT         420Wp       316Wp       425Wp       320Wp       430Wp       323Wp         32.16V       29.95V       32.37V       30.19V       32.58V       30.30V         13.06A       10.55A       13.13A       10.60A       13.20A       10.66A         38.74V       36.80V       38.95V       37.00V       39.16V       37.20V         13.51A       10.91A       13.58A       10.96A       13.65A       11.02A         21.51%       21.76%       22.02%       20.02%	JKM420N-54HL4-B       JKM425N-54HL4-B       JKM430N-54HL4-B       JKM435N         STC       NOCT       STC       NOCT       STC       NOCT       STC         420Wp       316Wp       425Wp       320Wp       430Wp       323Wp       435Wp         32.16V       29.95V       32.37V       30.19V       32.58V       30.30V       32.78V         13.06A       10.55A       13.13A       10.60A       13.20A       10.66A       13.27A         38.74V       36.80V       38.95V       37.00V       39.16V       37.20V       39.36V         13.51A       10.91A       13.58A       10.96A       13.65A       11.02A       13.72A         21.51%       21.76%       22.02%       22.       22.       22.         K         AMBIENT Temperature 25°C $AM = 1.5$ $AM = 1.5$ $= 5$ AMBIENT Temperature 20°C	JKM420N-54HL4-B       JKM425N-54HL4-B       JKM430N-54HL4-B       JKM435N-54HL4-B         STC       NOCT       STC       NOCT       STC       NOCT         420Wp       316Wp       425Wp       320Wp       430Wp       323Wp       435Wp       327Wp         32.16V       29.95V       32.37V       30.19V       32.58V       30.30V       32.78V       30.50V         13.06A       10.55A       13.13A       10.60A       13.20A       10.66A       13.27A       10.72A         38.74V       36.80V       38.95V       37.00V       39.16V       37.20V       39.36V       37.39V         13.51A       10.91A       13.58A       10.96A       13.65A       11.02A       13.72A       11.08A         21.51%       21.76%       22.02%       22.28%       22.28%       22.28%       22.28%	JKM420N-54HL4-B       JKM425N-54HL4-B       JKM430N-54HL4-B       JKM435N-54HL4-B       JKM440N         STC       NOCT       STC       NOCT       STC       NOCT       STC       NOCT       STC       S

\*Power measurement tolerance: ±3%

Solar

JinKO

The company reserves the final right for explanation on any of the information presented hereby. JKM400-420N-54HL4-B-F4-US

**BUILDING YOUR TRUST IN SOLAR. WWW.JINKOSOLAR.US** 





PACKAGING CONFIGURATION (Two pallets = One stack)

Pmax	-0.29%/°C
/oc	-0.25%/°C
sc	0.045%/°C
erature (NOCT)	45±2°C

-40°C~+85°C	
1000VDC	
25A	

31pcs/pallets, 62pcs/stack, 806pcs/40 HQ Container



		R/			
1007 JOHN	NIE DODD	s			
BLVD S CHARI	UITE 111 ESTON				
SC 2	29464				
EMAIL : info@e	-999-4837 empwrsolar	.com			
	· · · · · · · · · · · · · · · · · · ·				
REVIS	SIONS	<b>DEV</b>			
REVISION	DATE	REV			
TEVISION	00/24/2023	~			
	•				
DATE	6/23/2025				
		-00			
PROJECT NAM		-88			
	26				
	275 275				
	≥ °				
ーヨウ	A R				
	ED				
	^ ARI				
≥ S	1 -<				
R S∕ ∣	3 R A Y				
	48 QU				
	Ъ				
	DRAWN BY				
E\$	ESR				
SHEET NAME					
EQUI	EQUIPMENT				
SPECIFICATION					
	T 917E	·			
11" >	X 17"				
11" X	X 17"				

# 



# IQ8M and IQ8A Microinverters

Our newest IQ8 Microinverters are the industry's first microgrid-forming, softwaredefined microinverters with split-phase power conversion capability to convert DC power to AC power efficiently. The brain of the semiconductor-based microinverter is our proprietary application-specific integrated circuit (ASIC) which enables the microinverter to operate in grid-tied or off-grid modes. This chip is built in advanced 55nm technology with high speed digital logic and has super-fast response times to changing loads and grid events, alleviating constraints on battery sizing for home energy systems.



Part of the Enphase Energy System, IQ8 Series Microinverters integrate with the Enphase IQ Battery, Enphase IQ Gateway, and the Enphase App monitoring and analysis software.



Connect PV modules quickly and easily to the IQ8 Series Microinverters that has Integrated MC4 connectors.

Enphase 25 year limited warranty

IQ8 Series Microinverters redefine reliability standards with more than one million cumulative hours of power-on testing, enabling an industry-leading limited warranty of up to 25 years.



IQ8 Series Microinverters are UL Listed as PV Rapid Shut Down Equipment and conform with various regulations, when installed according to manufacturer's instructions.

© 2022 Enphase Energy. All rights reserved. Enphase, the Enphase logo, IQ8 Microinverters, and other names are trademarks of Enphase Energy, Inc. Data subject to change.

IQ8MA-MC4-DS-0003-02-EN-US-2022-08-23

#### Easy to install

• Lightweight and compact with plug-n-play connectors

DATA SHEET

- Power Line Communication
   (PLC) between components
- Faster installation with simple two-wire cabling

#### High productivity and reliability

- Produce power even when the grid is down\*
- More than one million cumulative hours of testing
- Class II double-insulated
   enclosure
- Optimized for the latest highpowered PV modules

#### Microgrid-forming

- Complies with the latest
   advanced grid support\*\*
- Remote automatic updates for the latest grid requirements
- Configurable to support a wide range of grid profiles
- Meets CA Rule 21 (UL 1741-SB)
  requirements

\* Only when installed with IQ System Controller 2, meets UL 1741.
\*\* IQ8M and IQ8A support split phase, 240V installations only.

# IQ8M and IQ8A Microinverters

∕∧∖

INPUT DATA (DC)		108M-72-M-US
Commonly used module pairings <sup>1</sup>	W	260 - 460
Module compatibility		60-cell / 120 half-cell, 66-cell / 132 h
MPPT voltage range	v	33 - 45
Operating range	v	25 - 5
Min / Max start voltage	v	30 / 3
Max input DC voltage	v	60
Max DC current <sup>2</sup> [module $I_{sc}$ ]	А	15
Overvoltage class DC port		П
DC port backfeed current	mA	0
PV array configuration		1 x 1 Ungrounded array; No additional DC side prctection requi
OUTPUT DATA (AC)		108M-72-M-US
Peak output power	VA	330
Max continuous output power	VA	325
Nominal (L-L) voltage / range <sup>3</sup>	V	240 / 211
Max continuous output current	А	1.35
Nominal frequency	Hz	60
Extended frequency range	Hz	50 -
AC short circuit fault current over 3 cycles	Arms	2
Max units per 20 A (L-L) branch circuit <sup>4</sup>		11
Total harmonic distortion		<5%
Overvoltage class AC port		111
AC port backfeed current	mA	30
Power factor setting		1.0
Grid-tied power factor (adjustable)		0.85 leading - 0
Peak efficiency	%	97.6
CEC weighted efficiency	%	97
Night-time power consumption	mW	60
MECHANICAL DATA		
Ambient temperature range		-40°C to +60°C (-
Relative humidity range		4% to 100% (c
DC Connector type		Stäubli
Dimensions (H x W x D)		212 mm (8.3") x 175 mm (
Weight		1.1 kg (2.4
Cooling		Natural convect
Approved for wet locations		Yes
Pollution degree		PD3
Enclosure		Class II double-insulated, corrosio
Environ. category / UV exposure rating		NEMA Туре 6
COMPLIANCE		
		CA Rule 21 (UL 1741-SB), UL 62109-1, UL1741 / IEEE1547, FCC Part 1
Certifications		This product is UL Listed as PV Rapid Shut Down Equipment and c 690.12 and C22.1-2018 Rule 64-218 Rapid Shutdown of PV System manufacturer's instructions.

 No enforced DC/AC ratio. See the compatibility calculator at https://link.enphase.com/module-compatibility.
 Maximum continuous input DC current is 10.6A. (3) Nominal voltage range can be extended beyond nominal if req by the utility. (4) Limits may vary. Refer to local requirements to define the number of microinverters per branch in you

	SOLA EMPWR SOLAR 1007 JOHNNIE DOE BLVD SUITE 111 CHARLESTON, 20101	
108A-72-M-US	SC 29464 TEL: 854-999-483 EMAIL : info@empwrsol	7 ar.com
half-cell and 72-cell / 144 half-cell		
36 - 45	REVISIONS	
58	REVISION 06/24/202	5 A
58		
{		
}		
}		
{		
ed; AC side protection requires max 20A per branch circuit		
108A-72-M-US		
366		
349		
145		
1.45		
38		
}		
4		
s (		
}		
}		
D.85 lagging	DATE:06/23/2025	
97.6		RESS
97.5		
}		
40°E to +140°E)	ш ≻:	1
ondensing)		
MC4		
6.9") x 30.2 mm (1.2")		
3 lbs)	AM AN SEC	
ion – no fans	S R S	ξ
}	4 5	ž
5	[   ū	-
n resistant polymeric enclosure	DRAWN BY	
/ outdoor	ESR	
	SHEET NAME	
	EQUIPMEN	т
onforms with NEC 2014, NEC 2017, and NEC 2020 section s, for AC and DC conductors, when installed according to	SPECIFICATI	NC
1	SHEET SIZE	
	ANSI B	
our area. 108MA-MC4-D5-0003-02-EN-U5-2022-08-23	<u> </u>	
}	SHEET NUMBER	
}	PV-11	

# 



IQ System Controller 3/3G

backup power.

IQ Load Controller

and prolong battery life.

Provides microgrid interconnection device

grid failures and seamlessly transitioning

(MID) functionality by automatically detecting

the home energy system from grid power to

Helps prioritize essential appliances during a

grid outage to optimize energy consumption

X-IQ-AM1-240-5-HDK X-IQ-AM1-240-5C-HDK X-IQ-AM1-240-5 X-IQ-AM1-240-5C

DATA SHEET

# IQ Combiner 5/5C

The IQ Combiner 5/5C consolidates interconnection equipment into a single enclosure and streamlines IQ Series Microinverters and IQ Gateway installation by providing a consistent, pre-wired solution for residential applications. IQ Combiner 5/5C uses wired control communication and is compatible with IQ System Controller 3/3G and IQ Battery 5P.

The IQ Combiner 5/5C, IQ Series Microinverters, IQ System Controller 3/3G, and IQ Battery 5P provide a complete grid-agnostic Enphase Energy System.



IQ Series Microinverters The high-powered smart grid-ready IQ Series Microinverters (IQ6, IQ7, and IQ8 Series) simplify the installation process.



IQ Battery 5P Fully integrated AC battery system. Includes six field-replaceable IQ8D-BAT Microinverters.



5-year limited warranty

\*For country-specific warranty information, see the https://enphase.com/installers/resources/warranty page.

© 2024 Enphase Energy. All rights reserved. Enphase, the e and CC logos, IQ, and certain other marks listed at <u>https://enphase.com/trademark-usage-guidelines</u> are trademarks of Enphase Energy, Inc. in the U.S. and other countries. Data subject to change.

#### Smart

- Includes IQ Gateway for communication and control
- Includes Enphase Mobile Connect (CELLMODEM-M1-06-SP-05), only with IQ Combiner 5C
- Supports flexible networking: Wi-Fi, Ethernet, or cellular
- Provides production metering (revenue grade) and consumption monitoring

#### Easy to install

- Mounts to one stud with centered brackets
- Supports bottom, back, and side conduit entries
- Supports up to four 2-pole branch circuits for 240 VAC plug-in breakers (not included)
- 80 A total PV branch circuits
- Factory installed hold-down kit
- Bluetooth-based Wi-Fi provisioning for easy Wi-Fi setup

#### Reliable

- Durable NRTL-certified NEMA type 3R
   enclosure
- 5-year limited warranty
- 2-year labor reimbursement program coverage included for IQ Combiner SKUs\*
- UL1741 Listed

# IQ Combiner 5/5C

#### MODEL NUMBER

IQ Combiner 5 (X-IQ-AM1-240-5/ X-IQ-AM1-240-5-HDK)	IQ Combiner 5 with IQ Gateway print production metering (ANSI C12.20 ±0 Battery monitoring (±2.5%). Includes IQ-AM1-240-5-HDK includes a factor circuit breakers mentioned in the <b>Ac</b>
IQ Combiner 5C (X-IQ-AM1-240-5C / X-IQ-AM1-240-5C-HDK)	IQ Combiner 5C with IQ Gateway pri PV production metering (ANSI C12.20 IQ Battery monitoring (±2.5%). Inclue (CELLMODEM-M1-06-SP-05) <sup>1</sup> . Inclue IQ-AM1-240-5C-HDK includes a fact circuit breakers mentioned in the <b>Ac</b>
WHAT'S IN THE BOX	
IQ Gateway printed circuit board	IQ Gateway is the platform for total e maintenance, and management of th
Busbar	80 A busbar with support for one IQ installing IQ Series Microinverters and
IQ Gateway breaker	Circuit breaker, 2-pole, 10 A/15 A
Production CT	Pre-wired revenue-grade solid-core
Consumption CT	Two consumption metering clamp CT
IQ Battery CT	One battery metering clamp CT, ship
CTRL board	Control board for wired communicat IQ Battery 5P
Enphase Mobile Connect (only with IQ Combiner 5C)	4G-based LTE-M1 cellular modem (CI data plan
Accessories kit	Spare control headers for the COMM
ACCESSORIES AND REPLACEMENT PARTS (NOT INCLU	IDED, ORDER SEPARATELY)
CELLMODEM-M1-06-SP-05	4G-based LTE-M1 cellular modem wit
CELLMODEM-M1-06-AT-05	4G-based LTE-M1 cellular modem wit
Circuit breakers (off-the-shelf)	Supports Eaton BR2XX, Siemens Q2 (XX represents 10, 15, 20, 30, 40, 50, BR240B circuit breakers compatible
Circuit breakers (provided by Enphase)	BRK-10A-2-240V, BRK-15A-2-240V, E BRK-20A-2P-240V-B (more details ir
XA-SOLARSHIELD-ES	Replacement solar shield for IQ Com
XA-ENV2-PCBA-5	IQ Gateway replacement printed circ
X-IQ-NA-HD-125A	Hold-down kit compatible with Eator required for X-IQ-AM1-240-5-HDK/X
XA-COMMS2-PCBA-5	Replacement COMMS-KIT-2 printed
ELECTRICAL SPECIFICATIONS	
Rating	80 A
System voltage and frequency	120/240 VAC or 120/208 VAC, 60 Hz
Busbar rating	125 A
Fault current rating	10 kAIC
Maximum continuous current rating (input from PV/ storage)	64 A
Branch circuits (solar and/or storage)	Up to four 2-pole Eaton BR, Siemens C (DG) breakers only (not included)
Maximum total branch circuit breaker rating (input)	80 A of distributed generation/95 A w
IQ Gateway breaker	10 A or 15 A rating GE/Siemens/Eaton

<sup>1</sup> A plug-and-play industrial-grade cell modem for systems of up to 60 microinverters. Available in the United States, Canada, Mexico cellular service in the installation area.

			R/		
	EMPWF	SOLAR	_		
nted circuit board for integrated revenue-grade PV ±0.5%), consumption monitoring (±2.5%), and IQ es a silver solar shield to deflect heat. ory installed hold-down kit compatible with all the ccessories and Replacement Parts section.	1007 JOHN BLVD S CHARI SC 3 TEL: 854 EMAIL : info@	1007 JOHNNIE DODDS BLVD SUITE 111 CHARLESTON, SC 29464 TEL: 854-999-4837 MAIL : info@empwrsolar.com			
rinted circuit board for integrated revenue-grade	REVI	SIONS			
20 ±0.5%), consumption monitoring (±2.5%), and udes Enphase Mobile Connect cellular modem udes a silver solar shield to deflect heat. ctory installed hold-down kit compatible with all the ccessories and Replacement Parts section.	DESCRIPTION REVISION	DATE 06/24/2025	REV A		
energy management for comprehensive, remote he Enphase Energy System					
2 Gateway breaker and four 20 A breakers for nd IQ Battery 5P					
e CT, accurate up to ±0.5%					
CTs, shipped with the box, accurate up to ±2.5%					
pped with the box, accurate up to $\pm 2.5\%$					
ation with IQ System Controller 3/3G and the					
CELLMODEM-M1-06-SP-05) with a 5-year T-Mobile					
MS-KIT-2 board					
vith a 5-year T-Mobile data plan					
vith a 5-year AT&T data plan					
2XX, and GE/ABB THQL21XX Series circuit breakers ), or 60). Also supports Eaton BR220B, BR230B, and e with the hold-down kit.	DATE:0	6/23/2025			
BRK-20A-2P-240V, BRK-15A-2P-240V-B, and in the "Accessories" section)	PROJECT NAI		ESS		
nbiner 5/5C		,≺, 275;			
rcuit board (PCB) for IQ Combiner 5/5C		N O			
on BR-B Series circuit breakers (with screws). Not (X-IQ-AM1-240-5C-HDK.		EDAF			
d circuit board (PCB) for IQ Combiner 5/5C		D AR			
	A A	ЯЕ Х-У			
	l о п	183 NUA			
		ruc ∠			
		NN BY			
Q, or GE/ABB THQL Series distributed generation	EQUI SPECIF	PMENT ICATIO	N		
with IQ Gateway breaker included	SHEE	T SIZE			
nincluded	AN	SI B			
ired to IQ Gateway	11"	X 17"			
ico, Puerto Rico, and the US Virgin Islands, where there is adequate	SHEET	NUMBER			
IQC-5-5C-DSH-00007-6.0-EN-US-2024-09-30	PV-	12			

#### ACCESSORIES AND REPLACEMENT PARTS (NOT INCLUDED, ORDER SEPARATELY)

200 A clamp-style current transformer for IO Battery metering, included with the box
200 A clamp-style current transformer for 12 battery metering, included with the box

Consumption monitoring CT (C	CT-200-CLAMP)	A pair of 200 A clamp-style current transformers is included with the box
IQ Battery metering CT		200 A clamp-style current transformer for IQ Battery metering, included with the box
MECHANICAL DATA		
Dimensions (W × H × D)		37.5 cm × 49.5 cm × 16.8 cm (14.75" × 19.5" × 6.63"). Height is 53.5 cm (21.06") with mounting brackets.
Weight		7.5 kg (16.5 lb)
Ambient temperature range		-40°C to 46°C (-40°F to 115°F)
Cooling		Natural convection, plus heat shield
Enclosure environmental rating	]	Outdoor, NRTL-certified, NEMA type 3R, polycarbonate construction
Wire sizes		<ul> <li>20 A to 50 A breaker inputs: 14 to 4 AWG copper conductors</li> <li>60 A breaker branch input: 4 to 1/0 AWG copper conductors</li> <li>Main lug combined output: 10 to 2/0 AWG copper conductors</li> <li>Neutral and ground: 14 to 1/0 copper conductors</li> <li>Always follow local code requirements for conductor sizing</li> </ul>
Communication (in-premise co	onnectivity)	Built-in CTRL board for wired communication with the IQ Battery 5P and the IQ System Controller 3/3G. Integrated power line communication for IQ Series Microinverters.
Altitude		Up to 2,600 meters (8,530 feet)
COMMUNICATION INTERFACE	S	
Integrated Wi-Fi		802.11b/g/n (dual band 2.4 GHz/5 GHz) for connecting the Enphase Cloud through the internet.
Wi-Fi range (recommended)		10 m (32.8 feet)
Bluetooth		BLE4.2, 10 m range to configure Wi-Fi SSID
Ethernet		Optional, 802.3, Cat5E (or Cat 6) UTP Ethernet cable (not included) for connecting to the Enphase Cloud through the internet.
Cellular/Mobile Connect		CELLMODEM-M1-06-SP-05 or CELLMODEM-M1-06-AT-05 (included with the IQ Combiner 5C)
Digital I/O		Digital input/output for grid operator control
USB 2.0		Mobile Connect, COMMS-KIT-01 for IQ Battery 3/3T/10/10T, COMMS-KIT-02 for IQ Battery 5P
Access point (AP) mode		For connection between the IQ Gateway and a mobile device running the Enphase Installer App
Metering ports		Up to two Consumption CTs, one IQ Battery CT, and one Production CT
Power line communication		90–110 kHz
Web API		See https://developer-v4.enphase.com
Local API		See <u>Guide for local API</u>
COMPLIANCE		
IQ Combiner with IQ Gateway		UL 1741, CAN/CSA C22.2 No. 107.1, Title 47 CFR, Part 15, Class B, ICES 003, NOM-208-SCFI-2016, UL 61010-1, CAN/CSA 22.2 No. 61010-1, IEEE 1547: 2018 (UL 1741-SB, 3rd Ed.), IEEE 2030.5/CSIP Compliant, Production metering: ANSI C12.20 accuracy class 0.5 (PV production)
COMPATIBILITY		
PV	Microinverters	IQ6, IQ7, and IQ8 Series Microinverters
	IQ System Controller	EP200G101-M240US00
COMMS-KIT-01 <sup>2</sup>	IQ System Controller 2	EP200G101-M240US01

ENCHARGE-10T-1P-NA

IQBATTERY-5P-1P-NA

SC200D111C240US01, SC200G111C240US01

ENCHARGE-3-1P-NA, ENCHARGE-10-1P-NA, ENCHARGE-3T-1P-NA,

# Accessories

#### Mobile Connect

4G-based LTE-M1 cellular modem with a 5-year data plan (CELLMODEM-M1-06-SP-05 for T-Mobile and CELLMODEM-M1-06-AT-05 for AT&T)



CT-200-SOLID



200 A revenue-grade solid-core Production CT with <0.5% error rate



<sup>2</sup> For information about IQ Combiner 5/5C compatibility with the 2<sup>nd</sup>-generation batteries, refer to the <u>compatibility matrix</u>. <sup>3.</sup> IQ Combiner 5/5C comes pre-equipped with COMMS-KIT-02.

IQ Battery

IQ Battery

COMMS-KIT-023

IQ System Controller 3

IQC-5-5C-DSH-00007-6.0-EN-US-2024-09-30

#### **Circuit breakers**

- BRK-10A-2-240V Circuit breaker, 2-pole, 10 A, Eaton BR210
- BRK-15A-2-240V Circuit breaker, 2-pole, 15 A, Eaton BR215
- BRK-20A-2P-240V Circuit breaker, 2-pole, 20 A, Eaton BR220
- BRK-15A-2P-240V-B Circuit breaker, 2-pole, 15 A,
- Eaton BR215B with hold-down kit support
- BRK-20A-2P-240V-B Circuit breaker, 2-pole, 20 A, Eaton BR220B with hold-down kit support

#### CT-200-CLAMP

200 A clamp-style consumption and battery metering CT with <2.5% error rate (replacement SKU)

EMPWR SOLAR S O L A R 1007 JOHNNIE DODDS BLVD SUITE 111 CHARLESTON, SC 29464 TEL: 854-999-4837 EMAIL : info@empwrsolar.com							
REVIS DESCRIPTION REVISION	DATE 06/24/2025	REV A					
PROJECT NAM	IE & ADDRI	ESS					
SAMUEL LEE RESIDENCE	483 RED CEDAR WY, FUQUAY-VARINA,NC 27526						
DRAV	DRAWN BY ESR						
EQUIF SPECIF	SHEET NAME EQUIPMENT SPECIFICATION						
SHEET SIZE ANSI B 11" X 17"							
SHEET N	NUMBER 13						



#### Solar Is Not Always Sunny

Over their lifetime, solar panels experience countless extreme weather events. Not just the worst storms in years, but the worst storms in 40 years. High winds capable of ripping panels from a roof, and snowfalls weighing enough to buckle a panel frame.

XR Rails are the structural backbone preventing these results. They resist uplift, protect against buckling and safely and efficiently transfer loads into the building structure. Their superior spanning capability requires fewer roof attachments, reducing the number of roof penetrations and the amount of installation time.



#### Force-Stabilizing Curve

Sloped roofs generate both vertical and lateral forces on mounting rails which can cause them to bend and twist. The curved shape of XR Rails is specially designed to increase strength in both directions while resisting the twisting. This unique feature ensures greater security during extreme weather and a longer system lifetime.

#### Compatible with Flat & Pitched Roofs



IronRidge offers a range of tilt leg options for flat roof mounting applications.

#### **Corrosion-Resistant Materials**

All XR Rails are made of 6000-series aluminum alloy, then protected with an anodized finish. Anodizing prevents surface and structural corrosion, while also providing a more attractive appearance.



# XR Rail Family

**Tech Brief** 

#### **XR Rail Family**

The XR Rail Family offers the strength of a curved rail in three targeted size design loads, while minimizing material costs. Depending on your location, t



#### **Rail Selection**

The table below was prepared in compliance with applicable engineering co based on the following criteria: ASCE 7-16, Gable Roof Flush Mount, Roof 2 Slope of 8 to 20 degrees and Mean Building Height of 30 ft. Visit IronRidge.

Load		Rail Span				
Snow (PSF)	Wind (MPH)	4'	5' 4"	6'	ī	
None	90					
	120					
	140	XR10		XR100		
	160					
20	90					
	120					
	140					
	160					
30	90					
	160					
40	90					
	160					
80	160					
120	160					

\*Table is meant to be a simplified span chart for conveying general rail capabilities. Use ap

es. Each size supp there is an XR Ra <b>XR1000</b> XR1000 is a heavyw solar mounting rails extreme climates an feet for commercial	EMPWF 1007 JOHN BLVD S CHARL SC : TEL: 854 EMAIL : info@ REVI DESCRIPTION REVISION	L A R SOLAR NIE DODDS UITE 111 LESTON, 29464 -999-4837 empwrsolar.cd SIONS DATE R 06/24/2025			
<ul> <li>12' spanning cap;</li> <li>Extreme load cap</li> <li>Clear anodized fii</li> <li>Internal splices and</li> <li>Internal splices and</li> <li>Ddes and standard</li> <li>Zones 1 &amp; 2e, Exj</li> <li>com for detailed of</li> </ul>	ability ability <sub>vailable</sub> ds.* Values are posure B, Roof certification letters.				
				8/23/2025	
8' 10'	12'		PROJECT NAI	ME & ADDRES	ss
XR100	0		SAMUEL LEE RESIDENCE	483 RED CEDAR WY, FUQUAY-VARINA,NC 27526	
			DRAWN BY ESR		
			EQUIPMENT SPECIFICATION		
approved certification letter	rs for actual design guidance.		SHEE AN 11"	SIB X 17"	
n. Version 1.20			SHEET PV-	NUMBER	



# **UFO Family of Components**

**Tech Brief** 

#### Simplified Grounding for Every Application

The UFO family of components eliminates the need for separate grounding hardware by bonding solar modules directly to IronRidge XR Rails. All system types that feature the UFO family-Flush Mount, Tilt Mount and Ground Mount-are fully listed to the UL 2703 standard.

UFO hardware forms secure electrical bonds with both the module and the rail, resulting in many parallel grounding paths throughout the system. This leads to safer and more reliable installations.



Stopper Sleeve The Stopper Sleeve snaps onto the UFO, converting it into a bonded end clamp.

Universal Fastening Object (UFO) The UFO securely bonds solar modules to XR Rails. It comes assembled and lubricated, and can fit a wide range of module heights.

**Bonded Splice** Each Bonded Splice uses

self-drilling screws to form a secure connection. No bonding strap needed.



Grounding Lug A single Grounding Lug connects an entire row of PV modules to the grounding conductor.



**Bonded Attachments** The bonding bolt attaches and bonds the L-foot to the rail. It is installed with the same socket as the rest of the system



А



Cross-Syst				
Feature	Flush Mount			
XR Rails	*			
UFO/Stopper	~			
Bonded Splice	~			
Grounding Lugs	1 per Row			
Microinverters & Power Optimizers	Enphase - M25 Darfon - N SolarEdge - P300,			
Fire Rating	Class A			
Modules	Tested or Evalu Refer to insta			





# QuickMount<sup>®</sup> RD Structural Screw



© 2022 IronRidge, Inc. All rights reserved. Visit www.ir-patents.com for patent information.

		/R			
EMPWR 1007 JOHN BLVD SI	EMPWR SOLAR 1007 JOHNNIE DODDS				
CHARL SC 2	ESTON, 9464				
TEL: 854- EMAIL : info@e	-999-4837 mpwrsolar	.com			
REVIS	SIONS				
DESCRIPTION	DATE	REV			
REVISION	00/24/2023	A			
DATE:06	23/2025	500			
PROJECT NAM		255			
	Υ, 752(				
日日の	NC 2				
	EDAI NA,N				
	O CE				
AN RES	REI Y-V				
0, 11	483 QUA				
	ЪŬ				
ESR					
SHEET NAME EQUIPMENT					
SPECIFICATION					
SHEET SIZE					
ANSI B 11" X 17"					
SHEET NUMBER					
SHEFT	NUMBER				
SHEET N	NUMBER				